

Framework for quantum modeling of fiber-optical networks: Part II

(Rev. 0.2.5: suggestions and corrections welcome)

John M. Myers

Gordon McKay Laboratory, Division of Engineering and Applied Sciences

Harvard University, Cambridge, Massachusetts 02138

(Dated: **31 May 2005**)

Abstract

We formulate quantum optics to include frequency dependence in the modeling of optical networks. Entangled light pulses available for quantum cryptography are entangled not only in polarization but also, whether one wants it or not, in frequency. We model effects of the frequency spectrum of faint polarization-entangled light pulses on detection statistics. For instance, we show how polarization entanglement combines with frequency entanglement in the variation of detection statistics with pulse energy.

Attention is paid not only to single-photon light states but also to multi-photon states. These are needed (1) to analyze the dependence of statistics on energy and (2) to help in calibrating fiber couplers, lasers and other devices, even when their desired use is for the generation of single-photon light.

PACS numbers: 03.65.-w, 03.65.Nk, 03.65.Ta, 84.30.Sk

Contents

PART I

1. Introduction	1
A. Quantum modeling	2
B. Aims in developing a framework	3
C. Approach	4
2. Modes, commutation rules, and light states	5
A. Single-photon state spread over multiple modes	9
B. Single-mode, multi-photon states	9
C. Broad-band coherent states	10
D. General state	11
E. Density matrices and traces	12
F. Partial traces of light states	13
G. Bi-photons: excitation in each of two orthogonal modes	15
3. Projections	16
A. Action of single-mode projections on multi-mode states	17
B. Multi-mode n -photon projector	17
C. Number operator	18
4. Loss and frequency dispersion	19
A. Loss cannot evade “no cloning”	19
5. Local quantum fields	20
A. Temporally local hermitian fields	21
B. Time, space, and dispersion	22
C. Projections in terms of local operators	23
6. Scattering matrix	23
A. Network without frequency mixing	24
7. Polarized and entangled light states	25
A. Fiber splice (without extraneous modes)	26
B. Coupler	27
C. Entangled states	27

D. Polarization-entangled states	28
8. Detection	29
A. Simple examples	30
B. Model of APD detector for quantum cryptography	31
C. Detection probabilities	33
D. Effect of time bounds on detection	36
E. Detection, energy, and photon subspaces	36
F. Preceding the APD detector by a beam-splitter	37
9. Polarization-entangled light for QKD	39
A. Bi-photon light states	39
B. Effect of a beam splitter	41
C. Effect of polarization rotation	41
PART II	
10. Modeling polarization-entangled QKD	43
A. Outcomes and probabilities	45
B. Light state	48
C. Energy profile	50
D. Calculation of probabilities	51
E. Case I: No frequency entanglement	56
F. Case II: Limit of extreme frequency entanglement as $\zeta \rightarrow \pm\infty$	58
G. Example numbers	59
Appendix A. Background	59
Appendix B. Operator Lemmas	60
Appendix C. Algebra of frequency-entangled operators	64
Appendix D. Fourier transforms in space and time	76
Appendix E. Expansion of light states in tensor products of broad-band coherent states	77
Appendix F. MATLAB programs for Section 10	78
References	97

PART II

10. MODELING POLARIZATION-ENTANGLED QKD

The language offered in the preceding sections supports a wide variety of models of the system shown in Fig. 5 [15], as well as of many other systems. Here we offer a first-cut model of a fiber-optic network that employs polarization-entangled light for quantum key distribution (QKD). At the present stage of development of quantum key distribution, the purpose of the modeling can hardly be to replace experiments: we lack convincing reasons, whether theoretical or experimental, on which to ground the guesswork necessary to generate numbers. Rather, we show how a model drawing on some questionable guesses can stimulate experiments.

Specifically, the model offered shows that if one assumes a Poisson distribution and one assumes a light state invariant under identical $SU(2)$ transformations of the light to both Alice and Bob, then such and such relations hold between energy, Bob's error rate, and Evangeline's entropy. These relations are the "conclusion part" of a statement that includes also an "if part." As remarked by Dave Pearson, any interesting conclusion makes the "if part" worth exploring, for instance by means of experiments. What evidence can we find in the lab for or against the assumption of $SU(2)$ invariance? For or against a Poisson distribution of photon number? Expecting to later challenge some of our own assumptions, we try to make our modeling modular, so that the assumptions can be changed, both to make room in the future for improvement, and to lay the ground for studies of sensitivity to these assumptions.

Now to business. Consider a simplified experiment to explore the relation between the energy of a polarization-entangled light pulse and various detection probabilities relevant to: (1) quantum bit error rate (QBER), (2) sifted bit rate, and (3) an eavesdropper's entropy. We start by being interested in the QKD topology shown in Fig. 5, in which Alice and Bob each operate passively to detect in two bases, with two detectors per basis.

For this first model we assume:

1. An ensemble of trials, one entangled pulse pair per trial.




FIG. 5: Polarization-entangled QKD system subjected to eavesdropping attack.

2. Pulses timed and detectors managed so that trapping, dead time, and other memory effects of detection are negligible.
3. **Light state** leaving transmitter, propagating in modes a_1, a_2 to Alice and in modes $\tilde{b}_1, \tilde{b}_2$ toward Bob, invariant under application of any given $SU(2)$ transformation to both the a -modes and the b -modes, as discussed below.
4. A probability of $1/2$ for Alice and Bob having matching bases.
5. Alice and Bob use “on-off” detectors as described in Sec. 8; the detector for mode a_j has a dark-count probability $p_{\text{dark}}(a_j)$ and an efficiency $\eta_{\text{det}}(a_j)$.
6. A fraction η_{trans} of the energy transmitted to Bob survives attenuation, as described by frequency-independent coupling to an undetected (undesired) mode.
7. Poisson distribution of photon number in the energy transmitted to Bob.
8. **Sifting rule:** Alice and Bob discard a bit except when (a) they each get one and only one detection, and (b) their bases match.

9. **Eavesdropping attack:** Evangeline sneaks a non-polarizing beam splitter into Bob's fiber to siphon off her choice of a fraction of the light into modes b_3 and b_4 that propagate in her fiber. This runs through a long, lossless, delay line to a rapidly variable polarization rotator, followed by a pair of perfect photon-number detectors. The delay line allows Evangeline to postpone detection until she has learned what basis Bob has used for his detection; she then rotates or not, as necessary to choose the basis that matches Bob's.

Much of the analysis is independent of assumptions 5 and 6; we indicate later where these assumptions enter.

To analyze the assumed eavesdropping attack, in which our attacker Evangeline knows Bob's basis, we do not need the whole setup of Fig. 5; we can simplify by leaving out the rotated bases, and the two beam splitters that support them, along with Evangeline's variable polarization rotator. This results in Fig. 6. One can think of the modes with subscripts 1 and 3 as 'vertically polarized' and those with subscripts 2 and 4 as 'horizontally polarized.' We model the variable coupler by which Evangeline taps off energy by an SU(2) transformation. For $j = 1, 2$ we have

$$\begin{bmatrix} b_j(\omega) \\ b_{j+2}(\omega) \end{bmatrix} = \begin{bmatrix} u & -v^* \\ v & u^* \end{bmatrix} \begin{bmatrix} \tilde{b}_j(\omega) \\ v_j(\omega) \end{bmatrix}, \quad (10.1)$$

where the v_j are vacuum modes assumed unexcited, and $|u|^2 + |v|^2 = 1$. Inverting this equation, we find

$$\tilde{b}_j(\omega) = u^* b_j(\omega) + v^* b_{j+2}(\omega). \quad (10.2)$$

A. Outcomes and probabilities

By an *elementary outcome* we mean a possible joint response of all the detectors involved. We view an elementary outcome as constituted from *components*, one component for each detector. In the context of the model presented here, an elementary outcome consists of a bit string for the modes for which detection is binary (such as APD detectors as modeled in Sec. 8), and a non-negative integer for each of Evangeline's two modes (that we imagine as having photon-counting detectors). Each possible joint response of the binary detectors can be




FIG. 6: Simplified network.

expressed by partitioning the set of modes subject to binary detection into a set $\mathbf{J}_0$ for which the response is ‘no-detect’ and a set $\mathbf{J}_1$ for which the response is ‘detect’; correspondingly any elementary outcome has the form $(\mathbf{J}_0, \mathbf{J}_1, k, m)$ where $k = N(b_3)$ and $m = N(b_4)$. The corresponding detection operator factors; given any normalized state vector $|\psi\rangle$,

$$\Pr(\mathbf{J}_0, \mathbf{J}_1, k, m) = \langle \psi | \mathbf{M}(\mathbf{J}_0, \mathbf{J}_1, k, m) | \psi \rangle, \quad (10.3)$$

with

$$\mathbf{M}(\mathbf{J}_0, \mathbf{J}_1, k, m) = P_k(b_3) P_m(b_4) \left(\prod_{x \in \mathbf{J}_0} M_0(x) \right) \left(\prod_{x \in \mathbf{J}_1} M_1(x) \right), \quad (10.4)$$

where $P_k(b_3)$ and $P_m(b_4)$ are projections and x ranges over modes in the lists $\mathbf{J}_0$ and $\mathbf{J}_1$.

When we want to ignore Evangeline’s detections, we have a non-elementary outcome $(\mathbf{J}_0, \mathbf{J}_1)$ with the corresponding probability

$$\Pr(\mathbf{J}_0, \mathbf{J}_1) = \sum_{k, m=0}^{\infty} \Pr(\mathbf{J}_0, \mathbf{J}_1, k, m). \quad (10.5)$$

In expressions for outcomes that enter calculations we will often write, in place of $(\mathbf{J}_0, \mathbf{J}_1)$, a list of all the modes in these sets in the order $(a_1 a_2 b_1 b_2)$ with a bar placed over the (undetected) modes that belong to $\mathbf{J}_0$. Thus an outcome specified by $\mathbf{J}_0 = \{a_2, b_1\}$ and $\mathbf{J}_1 = \{a_1, b_2\}$ will also be written $(a_1 \bar{a}_2 b_1 \bar{b}_2)$.

Only four such outcomes survive the assumed sifting rule that requires exactly one detection by Alice and exactly one detection by Bob. Because of the assumed light state, Bob takes ‘detect’ on b_1 to be a 1-bit for a quantum key, while Alice takes ‘detect’ not on a_1 but on a_2 for a 1-bit, etc. With this rule the four outcomes that survive sifting are related to ‘correct bit’ and ‘error’ as follows: $(a_1 \bar{a}_2 \bar{b}_1 b_2)$ and $(\bar{a}_1 a_2 b_1 \bar{b}_2)$ are correct from the standpoint of QKD, while $(\bar{a}_1 a_2 \bar{b}_1 b_2)$ and $(a_1 \bar{a}_2 b_1 \bar{b}_2)$ are errors.

The probability of a bit surviving sifting for cases in which the bases match is, in this simplified model,

$$\begin{aligned} & \Pr(\text{trial produces a sifted bit}) \\ &= \Pr(\bar{a}_1 a_2 \bar{b}_1 b_2) + \Pr(a_1 \bar{a}_2 b_1 \bar{b}_2) + \Pr(\bar{a}_1 a_2 b_1 \bar{b}_2) + \Pr(a_1 \bar{a}_2 \bar{b}_1 b_2). \end{aligned} \quad (10.6)$$

The probability of an error in a sifted bit is

$$\Pr(\text{bit error}|\text{sifted}) = \frac{\Pr(\bar{a}_1 a_2 \bar{b}_1 b_2) + \Pr(a_1 \bar{a}_2 b_1 \bar{b}_2)}{\Pr(\text{trial produces a sifted bit})}. \quad (10.7)$$

For trials that result in error-free bits, we want to know the degree to which Evangeline’s outcomes $N(b_3)$ and $N(b_4)$ leave her ignorant concerning Bob’s outcomes. This ignorance of Evangeline with respect to error-free bits is measured by Rényi entropy of order R . This R -entropy depends on the conditional probability that Bob received a 1, given Evangeline’s detector response (k, m) . This we denote

$$\begin{aligned} \text{Ev}(k, m) &\stackrel{\text{def}}{=} \Pr(\bar{a}_1 a_2 b_1 \bar{b}_2; k, m \mid \{\bar{a}_1 a_2 b_1 \bar{b}_2; k, m\} \text{ or } \{a_1 \bar{a}_2 \bar{b}_1 b_2; k, m\}) \\ &= \frac{\Pr(\bar{a}_1 a_2 b_1 \bar{b}_2; k, m)}{\Pr(\bar{a}_1 a_2 b_1 \bar{b}_2; k, m) + \Pr(a_1 \bar{a}_2 \bar{b}_1 b_2; k, m)}. \end{aligned} \quad (10.8)$$

Evangeline’s R -entropy given $N(b_3) = n$ and $N(b_4) = m$ is

$$\text{Ent}_R(k, m) = \frac{1}{1 - R} [(\text{Ev}(k, m))^R + (1 - \text{Ev}(k, m))^R]. \quad (10.9)$$

Evangeline’s average R -entropy on error-free bits is then

$$\text{AvEnt}_R = \frac{\sum_{k,m=0}^{\infty} [\Pr(\bar{a}_1 a_2 b_1 \bar{b}_2; k, m) + \Pr(a_1 \bar{a}_2 \bar{b}_1 b_2; k, m)] \text{Ent}_R(k, m)}{\Pr(\bar{a}_1 a_2 b_1 \bar{b}_2) + \Pr(a_1 \bar{a}_2 \bar{b}_1 b_2)}. \quad (10.10)$$

Altogether there are six types of outcomes: those with and without the distinction “ k, m ” for Evangeline’s detectors, and for each of these the general case of an arbitrary energy distribution and two special cases of the Poisson energy distribution and that of a single photon number n . Of course all these probabilities (and the R -entropy) depend on both the light state $|\psi\rangle$ and the parameters of the APD model of Alice’s and Bob’s detectors.

B. Light state

We formulate a family of states for entangled light, as is discussed in more detail in Appendix C. The calculations are complicated; here we carry them out for two limiting cases that are relatively simpler.

To begin rather generally, we are concerned with an otherwise arbitrary normalized state vector

$$|\psi\rangle = \sum_{n=0}^{\infty} C_n |\psi_n\rangle, \quad (10.11)$$

where the state $|\psi_n\rangle$ signifies n photons transmitted to Bob and

$$\sum_{n=0}^{\infty} |C_n|^2 = 1. \quad (10.12)$$

The index n for ‘photon number’ to Bob (which here will be the same as that for Alice) takes specific meaning when we assume a polarization-entangled light pulse invariant under matching $SU(2)$ transforms of both a -modes and $\tilde{b}$ -modes, for which

$$|\psi_n\rangle = \mathcal{N}(g_\zeta, n) [g_\zeta : (a_1 \tilde{b}_2 - a_2 \tilde{b}_1)^\dagger]^n |0\rangle, \quad (10.13)$$

with

$$g_\zeta : (a_1 \tilde{b}_2 - a_2 \tilde{b}_1)^\dagger \stackrel{\text{def}}{=} \int_{-\infty}^{\infty} d\omega_1 d\omega_2 g_\zeta(\omega_1, \omega_2) [a_1^\dagger(\omega_1) \tilde{b}_2^\dagger(\omega_2) - a_2^\dagger(\omega_1) \tilde{b}_1^\dagger(\omega_2)], \quad (10.14)$$

where we assume a family of functions $g_\zeta(\omega, \tilde{\omega})$ of the following form. For any real-valued functions $\phi(\omega)$ and $\tilde{\phi}(\tilde{\omega})$ and positive real parameters σ and $\tilde{\sigma}$, let

$$g_\zeta(\omega, \tilde{\omega}) = \frac{1}{\sqrt{\sigma\tilde{\sigma}}} e^{i\phi(\omega)} e^{i\tilde{\phi}(\tilde{\omega})} F\left(\zeta; \frac{\omega - \omega_0}{\sigma}, \frac{\tilde{\omega} - \tilde{\omega}_0}{\tilde{\sigma}}\right), \quad (10.15)$$

where we define

$$\begin{aligned} F(\zeta; x, y) &\stackrel{\text{def}}{=} \sqrt{\frac{2}{\pi}} \exp \left\{ -\frac{1}{2} \left[\left(\sqrt{\zeta^2 + 1} + \zeta \right) (x + y)^2 + \left(\sqrt{\zeta^2 + 1} - \zeta \right) (x - y)^2 \right] \right\} \\ &= \sqrt{\frac{2}{\pi}} \exp \left\{ - \left[\sqrt{\zeta^2 + 1} (x^2 + y^2) + 2\zeta xy \right] \right\}; \end{aligned} \quad (10.16)$$

regardless of the value of ζ ,

$$\int_{-\infty}^{\infty} dx dy |F(\zeta; x, y)|^2 = 1. \quad (10.17)$$

Thus for any choice of center frequencies ω_0 and $\tilde{\omega}_0$, bandwidth parameters σ and $\tilde{\sigma}$, and phase functions $\phi(\omega)$ and $\tilde{\phi}(\tilde{\omega})$, we get a family of g_ζ 's.

In Eq. (10.13), $\mathcal{N}(g_\zeta, n)$ is a normalization constant that makes $|\psi_n\rangle$ have unit norm, so that it is defined by

$$[\mathcal{N}(g_\zeta, n)]^2 = \langle 0 | [g_\zeta^* : (a_1 \tilde{b}_2 - a_2 \tilde{b}_1)]^n [g_\zeta : (a_1 \tilde{b}_2 - a_2 \tilde{b}_1)^\dagger]^n | 0 \rangle^{-1}. \quad (10.18)$$

Writing $(a_j b_k)$ for $g_\zeta^* : a_j b_k$, we have from Eq. (10.18)

$$\begin{aligned} [\mathcal{N}(g_\zeta, n)]^2 &= \langle 0 | [(a_1 \tilde{b}_2) - (a_2 \tilde{b}_1)]^n [(a_1 \tilde{b}_2) - (a_2 \tilde{b}_1)]^\dagger^n | 0 \rangle^{-1} \\ &= \langle 0 | \sum_{k=0}^n \binom{n}{k} (a_1 \tilde{b}_2)^k (-a_2 \tilde{b}_1)^{n-k} \sum_{\ell=0}^n \binom{n}{\ell} (a_1 \tilde{b}_2)^\dagger^\ell (-a_2 \tilde{b}_1)^\dagger^{n-\ell} | 0 \rangle^{-1} \\ &= \left\{ \sum_{k=0}^n \binom{n}{k}^2 \langle 0 | (a_1 \tilde{b}_2)^k (a_2 \tilde{b}_1)^{n-k} (a_1 \tilde{b}_2)^\dagger^k (a_2 \tilde{b}_1)^\dagger^{n-k} | 0 \rangle \right\}^{-1} \\ &= \left\{ n! \sum_{k=0}^n \binom{n}{k} \Xi_{g_\zeta}(k) \Xi_{g_\zeta}(n-k) \right\}^{-1}, \end{aligned} \quad (10.19)$$

where we define

$$\Xi_g(n) \stackrel{\text{def}}{=} \frac{1}{n!} \langle 0 | (g_\zeta^* : ab)^n (g_\zeta : a^\dagger b^\dagger)^n | 0 \rangle, \quad (10.20)$$

and the last equality in Eq. (10.19) comes from tensor-product factoring. Note that all that matters about $a(\omega)$ and $b(\omega)$ in this definition is that they are mutually orthogonal; any other pair would give the same value.

Re-expressing $|\psi_n\rangle$ in terms of detector modes per Eq. (10.2), one has for the light state

$$|\psi_n\rangle = \mathcal{N}(g_\zeta, n) [g_\zeta : (ua_1^\dagger b_2^\dagger + va_1^\dagger b_4^\dagger - ua_2^\dagger b_1^\dagger - va_2^\dagger b_3^\dagger)]^n | 0 \rangle. \quad (10.21)$$

When we write $(a_j^\dagger b_k^\dagger)$ as shorthand for $g_\zeta : a_j^\dagger b_k^\dagger$, this becomes

$$|\psi_n\rangle = \sum_{\substack{j,k,\ell,m=0 \\ j+k+\ell+m=n}}^n \mathcal{N}(g_\zeta, n) \frac{n!}{j!k!\ell!m!} u^{j+\ell} v^{k+m} (-1)^{\ell+m} (a_1^\dagger b_2^\dagger)^j (a_1^\dagger b_4^\dagger)^k (a_2^\dagger b_1^\dagger)^\ell (a_2^\dagger b_3^\dagger)^m |0\rangle. \quad (10.22)$$

C. Energy profile

We suppose that the light is generated by equipment close to Alice, so that the energy exposed to eavesdropping is in the $\tilde{b}$ -modes rather than in the a -modes. For a state of the form defined by Eqs. (10.11), (10.13), we want to express the expectation energy for modes $\tilde{b}_1$ and $\tilde{b}_2$, denoted

$$\text{Energy}(\tilde{b}_1, \tilde{b}_2) = \langle \psi | H(\tilde{b}_1, \tilde{b}_2) | \psi \rangle, \quad (10.23)$$

where for present purposes we approximate the hamiltonian operator

$$H(\tilde{b}_1, \tilde{b}_2) = \hbar \int_{-\infty}^{\infty} d\omega |\omega| [\tilde{b}_1^\dagger(\omega) \tilde{b}_1(\omega) + \tilde{b}_2^\dagger(\omega) \tilde{b}_2(\omega)] \quad (10.24)$$

for narrow-band signals by

$$H(\tilde{b}_1, \tilde{b}_2) \approx \hbar \omega_0 \int_{-\infty}^{\infty} d\omega [\tilde{b}_1^\dagger(\omega) \tilde{b}_1(\omega) + \tilde{b}_2^\dagger(\omega) \tilde{b}_2(\omega)], \quad (10.25)$$

where ω_0 is the carrier angular frequency, similar to that of Eq. (2.28). The commutation relation of Lemma (B14) of Appendix B leads then to

$$\text{Energy}(\tilde{b}_1, \tilde{b}_2) = \hbar \omega_0 \sum_{n=1}^{\infty} n |C_n|^2. \quad (10.26)$$

Denote the ‘mean photon number’ by

$$\mu \stackrel{\text{def}}{=} \frac{1}{\hbar \omega_0} \text{Energy}(\tilde{b}_1, \tilde{b}_2), \quad (10.27)$$

so that, from Eq. (10.26) we have

$$\mu = \sum_{n=1}^{\infty} n |C_n|^2. \quad (10.28)$$

To produce a dependence of probabilities on μ , we have to choose an energy profile, which means choosing the C_n . As a first cut, we will show consequences of assuming a Poisson distribution

$$\text{Assume: } |C_n|^2 = \frac{e^{-\mu} \mu^n}{n!}. \quad (10.29)$$

D. Calculation of probabilities

Lacking strong theoretical or experimental evidence to guide the choice of energy distribution of light for QKD, we arrange the modeling so that this distribution can be entered as a parameter. To this end we provide for modeling the contribution of individual values of photon number n . As remarked earlier, we want probabilities $\Pr(\mathbf{J}_0, \mathbf{J}_1, k, m)$ and $\Pr(\mathbf{J}_0, \mathbf{J}_1)$, i.e., with and without the “ k, m ” distinction; further we want each of these for the general case of an energy distribution $\mathbf{C} = \{|C_n|^2\}$ and for the two special cases of (1) a Poisson distribution and (2) an n -photon state. Altogether, this makes $2 \times 3 = 6$ types. Each of these six types will be expressed by a corresponding function $\mathcal{T}$; we will soon see $\mathcal{T}_{\mathbf{C}, km}$, $\mathcal{T}_{\mu, km}$, $\mathcal{T}_{n, km}$, $\mathcal{T}_{\mathbf{C}}$, $\mathcal{T}_{\mu}$, and $\mathcal{T}_n$. These $\mathcal{T}$ (for “total”) functions will be calculated as sums of corresponding functions $\mathcal{F}$ that are decorated with the same subscripts.

To start with, for purposes of calculating probabilities we break the state $|\psi_n\rangle$ down further in terms of the response of Evangeline’s photon-number detectors, assumed expressed by projection operators for modes b_3 and b_4 :

$$|\psi_n\rangle = \sum_{\substack{k, m=0 \\ k+m \leq n}}^n |\psi_{n, km}\rangle, \quad (10.30)$$

where

$$\begin{aligned} |\psi_{n, km}\rangle &\stackrel{\text{def}}{=} P_k(b_3) P_m(b_4) |\psi_n\rangle \\ &= \frac{\mathcal{N}(g_\zeta, n) n!}{k! m!} \sum_{j=0}^{n-k-m} \frac{u^{n-k-m} v^{k+m}}{j! (n-k-m-j)!} \\ &\quad \times (-1)^{n-k-j} (a_1^\dagger b_2^\dagger)^j (a_1^\dagger b_4^\dagger)^k (a_2^\dagger b_1^\dagger)^{n-k-m-j} (a_2^\dagger b_3^\dagger)^m |0\rangle. \end{aligned} \quad (10.31)$$

$|\psi\rangle$ and $|\psi_n\rangle$ but not $|\psi_{n,km}\rangle$ have unit norm

$$\sum_{k,m=0} \langle \psi_{n,km} | \psi_{n,km} \rangle = \langle \psi_n | \psi_n \rangle = 1. \quad (10.32)$$

As shorthand for products of detection operators we write

$$\begin{aligned} \mathbf{M}_0(\mathbf{J}_0) &= \prod_{x \in \mathbf{J}_0} M_0(x), \\ \mathbf{M}_1(\mathbf{J}_1) &= \prod_{x \in \mathbf{J}_1} M_1(x). \end{aligned} \quad (10.33)$$

The detection operators for Alice and Bob assumed here “respect” the numbers n , k , and m in the sense that, for any generic M of these operators,

$$\begin{aligned} \langle \psi | M | \psi \rangle &= \sum_{n=0}^{\infty} |C_n|^2 \langle \psi_n | M | \psi_n \rangle, \\ \langle \psi_n | M | \psi_n \rangle &= \sum_{\substack{k,m=0 \\ k+m \leq n}}^n \langle \psi_{n,km} | M | \psi_{n,km} \rangle. \end{aligned} \quad (10.34)$$

Thus from Eq. (10.3) we get, putting all this together,

$$\Pr(\mathbf{J}_0, \mathbf{J}_1, k, m) = \sum_{n=k+m}^{\infty} |C_n|^2 \langle \psi_{n,km} | \mathbf{M}_0(\mathbf{J}_0) \mathbf{M}_1(\mathbf{J}_1) | \psi_{n,km} \rangle, \quad (10.35)$$

where we adopt the convention that $|\psi_{n,km}\rangle = 0$ if $k + m > n$. For probabilities that are indifferent to Evangeline’s outcome components, we have

$$\Pr(\mathbf{J}_0, \mathbf{J}_1) = \sum_{n=0}^{\infty} |C_n|^2 \sum_{\substack{k,m=0 \\ k+m \leq n}}^n \langle \psi_{n,km} | \mathbf{M}_0(\mathbf{J}_0) \mathbf{M}_1(\mathbf{J}_1) | \psi_{n,km} \rangle. \quad (10.36)$$

This calculation is centered on

$$\langle \psi_{n,km} | \mathbf{M}_0(\mathbf{J}_0) \mathbf{M}_1(\mathbf{J}_1) | \psi_{n,km} \rangle. \quad (10.37)$$

From Eq. (8.23) we have

$$\langle \psi_{n,km} | \mathbf{M}_0(\mathbf{J}_0) \mathbf{M}_1(\mathbf{J}_1) | \psi_{n,km} \rangle = \mathcal{T}_{n,km}(\mathbf{J}_0, \mathbf{J}_1), \quad (10.38)$$

where we define

$$\mathcal{T}_{n,km}(\mathbf{J}_0, \mathbf{J}_1) \stackrel{\text{def}}{=} (-1)^{\#(\mathbf{J}_0)} \sum_{\mathbf{X} \subset \mathbf{J}_1} \mathcal{F}_{n,km}(\mathbf{J}_0 \| \mathbf{X}), \quad (10.39)$$

with $\mathcal{F}_{n,km}$ defined by

$$\mathcal{F}_{n,km}(\mathbf{J}_0 \parallel \mathbf{X}) \stackrel{\text{def}}{=} (-1)^{\#(\mathbf{J}_0 \parallel \mathbf{X})} \langle \psi_{n,km} | \mathbf{M}_0(\mathbf{J}_0 \parallel \mathbf{X}) | \psi_{n,km} \rangle. \quad (10.40)$$

(Note that the sum is over all subsets of $\mathbf{J}_1$, including both $\mathbf{J}_1$ itself and the empty set ϕ .)

In our numerical programs it proved convenient to code the arguments $\mathcal{F}(\mathbf{J}_0 \parallel \mathbf{X})$ (of any type of $\mathcal{F}$ -function) by a 4-bit vector ordered by all the modes a_1, a_2, b_1, b_2 , with a 1 if the mode belongs to $\mathbf{J}_0 \parallel \mathbf{X}$ and zero otherwise. Thus $\mathcal{F}(\bar{a}_1, \bar{a}_2, \bar{b}_1)$ would be coded as $\mathcal{F}(1110)$. For example, for one of the probabilities that enter Eq. (10.8), we have

$$\begin{aligned} \mathcal{T}_{n,km}(\bar{a}_1 a_2 b_1 \bar{b}_2) \\ &= \mathcal{F}_{n,km}(\bar{a}_1, \bar{b}_2) + \mathcal{F}_{n,km}(\bar{a}_1, \bar{b}_2, \bar{a}_2) + \mathcal{F}_{n,km}(\bar{a}_1, \bar{b}_2, \bar{b}_1) + \mathcal{F}_{n,km}(\bar{a}_1, \bar{b}_2, \bar{a}_2, \bar{b}_2) \\ &= \mathcal{F}_{n,km}(1001) + \mathcal{F}_{n,km}(1101) + \mathcal{F}_{n,km}(1011) + \mathcal{F}_{n,km}(1111). \end{aligned} \quad (10.41)$$

This is convenient because of a trick of using a second coding scheme for coding the argument of the $\mathcal{T}$ -function: The $\mathcal{T}$ -function argument is coded (‘negatively’ so to speak) by assigning a 1 if the mode appears with a bar over it and a 0 otherwise. With these two coding schemes, the code for the $\mathcal{T}$ -function argument becomes the code for the first $\mathcal{F}$ -function argument, and the rest of the $\mathcal{F}$ -function arguments are obtained by “filling in zeros” in all possible ways.

In this way one evaluates Eq. (10.37) using only M_0 operators. Drawing on the prescription of Proposition (8.16), to calculate $\mathcal{F}_{n,km}$ we define

$$|\phi_{n,km}(\alpha_1, \alpha_2, \beta_1, \beta_2)\rangle, \quad (10.42)$$

the vector obtained from the expression in Eq. (10.31) for $|\psi_{n,km}\rangle$ by replacing, for $j = 1, 2$, $a_j^\dagger(\omega)$ by $\alpha_j^{1/2} a_j^\dagger(\omega)$ and $b_j^\dagger(\omega)$ by $\beta_j^{1/2} b_j^\dagger(\omega)$. This substitution yields

$$\begin{aligned} &\langle \phi_{n,km}(\alpha_1, \alpha_2, \beta_1, \beta_2) | \phi_{n,km}(\alpha_1, \alpha_2, \beta_1, \beta_2) \rangle \\ &= \frac{|\mathcal{N}(g_\zeta, n)|^2 n!^2}{k!^2 m!^2} \sum_{j=0}^{n-k-m} \frac{|u|^{2(n-k-m)} (1 - |u|^2)^{k+m}}{j!^2 (n-k-m-j)!^2} \alpha_1^{j+k} \alpha_2^{n-k-j} \beta_1^{n-k-m-j} \beta_2^j \chi, \end{aligned} \quad (10.43)$$

where we define

$$\chi = \langle 0 | (a_1 b_2)^j (a_1 b_4)^k (a_2 b_1)^{n-k-m-j} (a_2 b_3)^m | (a_1^\dagger b_2^\dagger)^j (a_1^\dagger b_4^\dagger)^k (a_2^\dagger b_1^\dagger)^{n-k-m-j} (a_2^\dagger b_3^\dagger)^m | 0 \rangle$$

$$= \langle 0|(a_1 b_2)^j (a_1 b_4)^k (a_1^\dagger b_2^\dagger)^j (a_1^\dagger b_4^\dagger)^k |0\rangle \langle 0|(a_2 b_1)^{n-k-m-j} (a_2 b_3)^m (a_2^\dagger b_1^\dagger)^{n-k-m-j} (a_2^\dagger b_3^\dagger)^m |0\rangle, \quad (10.44)$$

with the factorization coming from a tensor product. From Proposition (B18) we have

$$\langle 0|(a_1 b_2)^j (a_1 b_4)^k (a_1^\dagger b_2^\dagger)^j (a_1^\dagger b_4^\dagger)^k |0\rangle = \frac{j!k!}{(j+k)!} \langle 0|(ab)^{j+k} (a^\dagger b^\dagger)^{j+k} |0\rangle = j!k! \Xi_{g_\zeta}(j+k), \quad (10.45)$$

where, as in Appendix C, we define

$$\Xi_{g_\zeta}(n) \stackrel{\text{def}}{=} \frac{1}{n!} \langle 0|(ab)^n (a^\dagger b^\dagger)^n |0\rangle. \quad (10.46)$$

As a result, we have

$$\chi = j!k!(n-k-m-j)!m! \Xi_{g_\zeta}(j+k) \Xi_{g_\zeta}(n-k-j), \quad (10.47)$$

whence it follows that

$$\begin{aligned} & \langle \phi_{n,km}(\alpha_1, \alpha_2, \beta_1, \beta_2) | \phi_{n,km}(\alpha_1, \alpha_2, \beta_1, \beta_2) \rangle \\ &= \frac{|\mathcal{N}(g_\zeta, n)|^2 n!^2}{k!m!} |u|^{2(n-k-m)} (1-|u|^2)^{k+m} \\ & \quad \times \sum_{j=0}^{n-k-m} \frac{\Xi_{g_\zeta}(j+k) \Xi_{g_\zeta}(n-k-j)}{j!(n-k-m-j)!} \alpha_1^{j+k} \alpha_2^{n-k-j} \beta_1^{n-k-m-j} \beta_2^j \\ &= \mathcal{G}_{n,km}(w, x, y, z), \end{aligned} \quad (10.48)$$

where we define

$$\begin{aligned} & \mathcal{G}_{n,km}(w, x, y, z) \\ & \stackrel{\text{def}}{=} \frac{|\mathcal{N}(g_\zeta, n)|^2 n!^2}{k!m!} \sum_{j=0}^{n-k-m} \frac{\Xi_{g_\zeta}(j+k) \Xi_{g_\zeta}(n-k-j)}{j!(n-k-m-j)!} w^j x^k y^{n-k-m-j} z^m, \end{aligned} \quad (10.49)$$

with

$$w = \alpha_1 \beta_2 |u|^2, \quad x = \alpha_1 (1-|u|^2), \quad y = \alpha_2 \beta_1 |u|^2, \quad z = \alpha_2 (1-|u|^2). \quad (10.50)$$

Thus for $\mathbf{L} \subset \{a_1, a_2, b_1, b_2\}$, the recipe of Sec. 8 yields for the $\mathcal{F}_{n,km}$ of Eq. (10.40)

$$\mathcal{F}_{n,km}(\mathbf{L}) \stackrel{\text{def}}{=} (-1)^{\#(\mathbf{L})} \left(\prod_{x \in \mathbf{L}} [1 - p_{\text{dark}}(x)] \right) \mathcal{G}_{n,km}(w, x, y, z) |_{\text{Eval}}, \quad (10.51)$$

with $\mathcal{G}_{n,km}(w, x, y, z)$ evaluated, using Eq. (10.50), according to:

$$\begin{aligned}\alpha_j &= \begin{cases} 1 - \eta_{\text{det}}(a_j), & \text{if } a_j \in \mathbf{L}, \\ 1, & \text{otherwise,} \end{cases} \\ \beta_j &= \begin{cases} 1 - \eta_{\text{det}}(b_j)\eta_{\text{trans}}, & \text{if } b_j \in \mathbf{L}, \\ 1, & \text{otherwise.} \end{cases}\end{aligned}\quad (10.52)$$

The remaining probabilities that we need to evaluate are less fine-grained; they are

$$\langle \psi_n | \mathbf{M}(\bar{a}_1, \bar{b}_2; a_2, b_1) | \psi_n \rangle = \sum_{\substack{k,m=0 \\ k+m \leq n}} \langle \psi_{n,km} | \mathbf{M}(\bar{a}_1, \bar{b}_2; a_2, b_1) | \psi_{n,km} \rangle, \quad (10.53)$$

along with $\langle \psi_n | \mathbf{M}(\bar{a}_2, \bar{b}_1; a_1, b_2) | \psi_n \rangle$ and the two error outcomes $\langle \psi_n | \mathbf{M}(\bar{a}_2, \bar{b}_2; a_1, b_1) | \psi_n \rangle$ and $\langle \psi_n | \mathbf{M}(\bar{a}_1, \bar{b}_1; a_2, b_2) | \psi_n \rangle$. These are calculated by replacing $\mathcal{T}_{n,km}$ by

$$\mathcal{T}_n(\mathbf{J}_0, \mathbf{J}_1) \stackrel{\text{def}}{=} \sum_{\substack{k,m=0 \\ k+m \leq n}} \mathcal{T}_{n,km}(\mathbf{J}_0, \mathbf{J}_1), \quad (10.54)$$

the calculation of which is streamlined by noticing, in analogy to Eq. (10.39),

$$\mathcal{T}_n(\mathbf{J}_0, \mathbf{J}_1) = \sum_{\mathbf{X} \subset \mathbf{J}_1} (-1)^{\#(\mathbf{X})} \mathcal{F}_n(\mathbf{J}_0 \| \mathbf{X}), \quad (10.55)$$

with

$$\mathcal{F}_n(\mathbf{L}) \stackrel{\text{def}}{=} \sum_{\substack{k,m=0 \\ k+m \leq n}} \mathcal{F}_{n,km}(\mathbf{L}), \quad (10.56)$$

evaluated using

$$\mathcal{G}_n(w, x, y, z) \stackrel{\text{def}}{=} \sum_{\substack{k,m=0 \\ k+m \leq n}} \mathcal{G}_{n,km}(w, x, y, z). \quad (10.57)$$

Letting $r = j + k$ and re-ordering the sum and using Eq. (10.49), one finds

$$\begin{aligned}\mathcal{G}_n(w, x, y, z) &= |\mathcal{N}(g_\zeta, n)|^2 n!^2 \sum_{r=0}^n \Xi_{g_\zeta}(r) \Xi_{g_\zeta}(n-r) \sum_{j=0}^r \frac{w^j x^{r-j}}{j!(r-j)!} \sum_{\ell=0}^{n-r} \frac{y^\ell z^{n-r-\ell}}{\ell!(n-r-\ell)!} \\ &= |\mathcal{N}(g_\zeta, n)|^2 n!^2 \sum_{r=0}^n \frac{\Xi_{g_\zeta}(r) \Xi_{g_\zeta}(n-r)}{r!(n-r)!} (w+x)^r (y+z)^{n-r}.\end{aligned}\quad (10.58)$$

Turning to the probabilities that require summing over a distribution of energies, we use Eq. (10.38) to make Eq. (10.35) explicit:

$$\Pr(\mathbf{J}_0, \mathbf{J}_1, k, m) = \mathcal{T}_{\mathbf{C}, km} \stackrel{\text{def}}{=} \sum_{n=k+m}^{\infty} |C_n|^2 \mathcal{T}_{n, km}, \quad (10.59)$$

where we recognize that $\mathcal{F}_{n, km}$ and $\mathcal{T}_{n, km}$ are zero if $n < k + m$. Similarly Eq. (10.36) becomes

$$\Pr(\mathbf{J}_0, \mathbf{J}_1) = \mathcal{T}_{\mathbf{C}}(\mathbf{J}_0, \mathbf{J}_1) \stackrel{\text{def}}{=} \sum_{n=k+m}^{\infty} |C_n|^2 \mathcal{T}_n(\mathbf{J}_0, \mathbf{J}_1). \quad (10.60)$$

Given an energy profile $\mathbf{C} \stackrel{\text{def}}{=} \{|C_n|^2\}$, one evaluates Eq. (10.35) efficiently by defining

$$\mathcal{G}_{\mathbf{C}, km}(w, x, y, z) = \sum_{n=k+m}^{\infty} |C_n|^2 \mathcal{G}_{n, km}(w, x, y, z), \quad (10.61)$$

and observing that, analogous to Eq. (10.51),

$$\mathcal{F}_{\mathbf{C}, km}(\mathbf{L}) = (-1)^{\#(\mathbf{L})} \left(\prod_{x \in \mathbf{L}} [1 - p_{\text{dark}}(x)] \right) \mathcal{G}_{\mathbf{C}, km}(w, x, y, z) |_{\text{Eval}}, \quad (10.62)$$

evaluated by the prescription of Eq. (10.52).

For evaluating $\Pr(\mathbf{J}_0, \mathbf{J}_1)$ (for use when one is indifferent to Evangeline's outcome components), we introduce the analogous

$$\mathcal{F}_{\mathbf{C}}(\mathbf{L}) = (-1)^{\#(\mathbf{L})} \left(\prod_{x \in \mathbf{L}} [1 - p_{\text{dark}}(x)] \right) \mathcal{G}_{\mathbf{C}}(w, x, y, z) |_{\text{Eval}}, \quad (10.63)$$

evaluated by the prescription of Eq. (10.52), but with

$$\mathcal{G}_{\mathbf{C}}(w, x, y, z) = \sum_{n=k+m}^{\infty} |C_n|^2 \mathcal{G}_n(w, x, y, z). \quad (10.64)$$

E. Case I: No frequency entanglement

The absence of frequency entanglement is exemplified by $g_{\text{I}}(\omega, \tilde{\omega}) = f(\omega)h(\tilde{\omega})$, normalized so that $\iint d\omega d\tilde{\omega} |g(\omega, \tilde{\omega})|^2 = \int d\omega |f(\omega)|^2 = \int d\tilde{\omega} |h(\tilde{\omega})|^2 = 1$. Denoting $\mathcal{N}(g_{\zeta}, n)$ evaluated at $\zeta = 0$ by $\mathcal{N}_{\text{I}}(n)$, we have from the rules for Case I at the end of Appendix C applied to Eq. (10.19)

$$|\mathcal{N}_{\text{I}}(n)|^2 = \left(n! \sum_{k=0}^n \binom{n}{k} k!(n-k)! \right)^{-1} = \frac{1}{(n+1)n!^2}. \quad (10.65)$$

From Lemma (C72) of Appendix C, we have

$$\Xi_I(n) \stackrel{\text{def}}{=} \frac{1}{n!} \langle 0 | \left(a \cdot \frac{g_I^*}{\cdot} \cdot b \right)^n \left(a^\dagger \cdot \frac{g_I}{\cdot} \cdot b^\dagger \right)^n | 0 \rangle = n!. \quad (10.66)$$

With these specializations, Eq. (10.49) becomes

$$\begin{aligned} \mathcal{G}_{n,km}^{(I)}(w, x, y, z) \\ = \frac{1}{(n+1)k!m!} x^k z^m \sum_{j=0}^{n-k-m} \frac{(j+k)!(n-k-j)!}{j!(n-k-m-j)!} w^j y^{n-k-m-j}. \end{aligned} \quad (10.67)$$

For reference, we note that this involves a hypergeometric function [16]

$$\begin{aligned} \mathcal{G}_{n,km}^{(I)}(w, x, y, z) \\ = \frac{(n-k)!}{(n+1)m!(n-k-m)!} x^k y^{n-k-m} z^m {}_2F_1 \left(k+1, k+m-n; k-n; \frac{w}{y} \right). \end{aligned} \quad (10.68)$$

For use when one is indifferent to Evangeline's outcome components, one finds $\mathcal{G}_n^{(I)}(w, x, y, z)$ analytically from Eq. (10.58) as

$$\begin{aligned} \mathcal{G}_n^{(I)}(w, x, y, z) &\stackrel{\text{def}}{=} \sum_{\substack{k,m=0 \\ k+m \leq n}} \mathcal{G}_{n,km}^{(I)}(w, x, y, z) \\ &= \frac{(y+z)^{n+1} - (w+x)^{n+1}}{(n+1)(y+z-w-x)}. \end{aligned} \quad (10.69)$$

In numerical work, we encounter the limit as $y+z-w-x \rightarrow 0$, in which case this becomes

$$\lim_{y+z-w-x \rightarrow 0} \mathcal{G}_n^{(I)}(w, x, y, z) = (y+z)^n. \quad (10.70)$$

For the special case of the Poisson energy distribution, we sum Eq. (10.69) to obtain

$$\begin{aligned} \mathcal{G}_\mu^{(I)}(w, x, y, z) &\stackrel{\text{def}}{=} e^{-\mu} \sum_{n=0}^{\infty} \frac{\mu^n}{n!} \mathcal{G}_n^{(I)}(w, x, y, z) \\ &= \frac{e^{-\mu}}{y+z-w-x} \frac{1}{\mu} [e^{\mu(y+z)} - e^{\mu(w+x)}]. \end{aligned} \quad (10.71)$$

In numerical work, we again encounter the limit as $y+z-w-x \rightarrow 0$, in which case this becomes

$$\lim_{y+z-w-x \rightarrow 0} \mathcal{G}_\mu^{(I)}(w, x, y, z) = e^{-\mu(1-y-z)}. \quad (10.72)$$

F. Case II: Limit of extreme frequency entanglement as $\zeta \rightarrow \pm\infty$

It makes no sense to ask for the limit of g_ζ ; however, we explore how the probabilities behave in the limit of large values of $|\zeta|$. Denoting $\mathcal{N}(g_\zeta, n)$ in the limit as $\zeta \rightarrow \pm\infty$ by $\mathcal{N}_{\text{II}}(n)$, we have from the rules for Case II at the end of Appendix C applied to Eq. (10.19)

$$|\mathcal{N}_{\text{II}}(n)|^2 = \frac{2^{-n}}{n!}, \quad (10.73)$$

which (in its power of $n!$) differs from the preceding case. From Lemma (C79) of Appendix C we have

$$\Xi_{\text{II}}(n) \stackrel{\text{def}}{=} \lim_{\zeta \rightarrow \pm\infty} \frac{1}{n!} \langle 0 | \left(a \cdot \overset{*}{\underset{\rightarrow}{g}} \cdot b \right)^n \left(a^\dagger \cdot \vec{g} \cdot b^\dagger \right)^n | 0 \rangle = 1. \quad (10.74)$$

With these specializations, Eq. (10.49) becomes, for Case II,

$$\begin{aligned} \mathcal{G}_{n,km}^{(\text{II})}(w, x, y, z) &= \frac{2^{-n}n!}{k!m!} \sum_{j=0}^{n-k-m} \frac{1}{j!(n-k-m-j)!} w^j x^k y^{n-k-m-j} z^m \\ &= \frac{2^{-n}n!}{k!m!(n-k-m)!} x^k z^m (w+y)^{n-k-m}. \end{aligned} \quad (10.75)$$

Putting this together with the Poisson distribution for energy yields

$$\begin{aligned} \mathcal{G}_{\mu,km}^{(\text{II})}(w, x, y, z) &\stackrel{\text{def}}{=} \sum_{n=k+m}^{\infty} |C_n|^2 \mathcal{G}_{n,km}^{(\text{II})}(w, x, y, z) \\ &= e^{-\mu} \sum_{n=k+m}^{\infty} \left(\frac{\mu}{2} \right)^n \frac{x^k z^m (w+y)^{n-k-m}}{k!m!(n-k-m)!} \\ &= \exp \left[-\frac{\mu}{2}(2-w-y) \right] \left(\frac{\mu}{2} \right)^{k+m} \frac{x^k z^m}{k!m!}. \end{aligned} \quad (10.76)$$

For the sum of these over k, m , Eqs. (10.74) and (10.58) imply

$$\mathcal{G}_n^{(\text{II})}(w, x, y, z) = 2^{-n} (w+x+y+z)^n. \quad (10.77)$$

Summing over all n weighted by $|C_n|^2$ yields, for use in calculating probabilities for Alice and Bob regardless of Evangeline's outcome components,

$$\begin{aligned} \mathcal{G}_\mu^{(\text{II})}(w, x, y, z) &\stackrel{\text{def}}{=} e^{-\mu} \sum_{n=k+m}^{\infty} \frac{\mu^n}{n!} 2^{-n} (w+x+y+z)^n \\ &= \exp \left[-\frac{\mu}{2}(2-w-x-y-z) \right]. \end{aligned} \quad (10.78)$$




FIG. 7: Probability of error versus μ , for $\zeta = 0, 1, 10, 100, 1000$, and $\zeta \rightarrow \infty$.

G. Example numbers

Figure 7 shows the probability of error vs. μ for several values of ζ . This shows explicitly how changing frequency entanglement ζ changes the dependence of the probability of error on μ . Other cases can be generated from the MATLAB programs listed in Appendix F.

APPENDIX A: BACKGROUND

1. Commutation relation

The commutation relation was chosen by analogy with that for the harmonic oscillator. One can ask if the δ -function should be multiplied by a factor that depends on propagation constant.

We answer “no” for the following reason. We want the energy of a 1-photon light state having a narrow frequency spectrum centered at ω_0 to be close to $\hbar|\omega_0|$. Taking such a state as an in-state to a fiber-vacuum interface results in an out-state of the same frequency but different wavelength. In order for energy to be conserved, we need the energy calculated for a 1-photon state to be independent of variations in wavelength at a given frequency. That rules out any factor in the commutation relation that depends on the in-fiber propagation constant.

2. Units

$a(\omega)$ in units of $(\text{seconds})^{1/2}$; a_f is dimensionless for a normalized function f which has dimension of $\text{sec}^{1/2}$.

Viewing a single-mode of a path as a transmission line, we need an operator corresponding to voltage (analogous to the electric-field operator of quantum electrodynamics).

3. Quantum mechanics stripped of space and time

Often it is convenient to make a preliminary analysis that skips all the integrals over frequency by treating quantum states in a toy Hilbert space of finite dimension, which means that space and time are collapsed to zero dimensions. (That still leaves polarization, for example.) This procedure is equivalent to an analysis allowing for frequency for certain calculations, namely when the frequency functions involved are all mutually orthogonal. An example is Eq. (2.29).

APPENDIX B: OPERATOR LEMMAS

For any two operators A and B let $[A, B] \stackrel{\text{def}}{=} AB - BA$.

Lemma: For any operators A, B, C ,

$$\begin{aligned} [A, BC] &= [A, B]C + B[A, C], \\ [AB, C] &= [A, C]B + A[B, C]. \end{aligned} \tag{B1}$$

Lemma: If $[B, C] = 0$, then

$$\begin{aligned} [[A, B], C] &= [[A, C], B], \\ [C, [B, A]] &= [B, [C, A]]. \end{aligned} \quad (\text{B2})$$

Lemma: For any four operators A, B, C, D ,

$$[AB, CD] = A[B, C]D + [A, C]BD + C[A, D]B + CA[B, D]. \quad (\text{B3})$$

Lemma: For $n = 1, 2, \dots$,

$$[A, B^n] = \sum_{k=1}^n B^{k-1} [A, B] B^{n-k}. \quad (\text{B4})$$

Lemma: If $A|0\rangle = B|0\rangle = 0$, then

$$\langle 0|ABA^\dagger B^\dagger|0\rangle = \langle 0|A[B, A^\dagger]B^\dagger|0\rangle + \langle 0|[A, A^\dagger][B, B^\dagger]|0\rangle. \quad (\text{B5})$$

Lemma: For any two operators A and $B^\dagger$, if $[[[A, B^\dagger], B^\dagger], B^\dagger] = 0$, then

$$[A, B^{\dagger n}] = n \left\{ \frac{n-1}{2} B^{\dagger(n-2)} [[A, B^\dagger], B^\dagger] + B^{\dagger(n-1)} [A, B^\dagger] \right\}. \quad (\text{B6})$$

Proof: $[A, B^{\dagger n}] = \sum_{k=1}^n B^{\dagger(k-1)} [A, B^\dagger] B^{\dagger(n-k)}$ and

$$\begin{aligned} [A, B^\dagger] B^{\dagger(n-k)} &= B^{\dagger(n-k)} [A, B^\dagger] + [[A, B^\dagger], B^{\dagger(n-k)}] \\ &= B^{\dagger(n-k)} [A, B^\dagger] + \sum_{j=1}^{n-k} B^{\dagger(n-k-1)} [[A, B^\dagger], B^\dagger], \end{aligned}$$

whence the lemma follows. $\square$

Lemma: If $[[[A, A^\dagger], A^\dagger], A^\dagger] = 0$ and $A|0\rangle = 0$, then

$$\langle 0|A^n A^{\dagger n}|0\rangle = \frac{n(n-1)}{2} \langle 0|A^{n-1} A^{\dagger(n-2)} [[A, A^\dagger], A^\dagger]|0\rangle + n \langle 0|A A^\dagger|0\rangle \langle 0|A^{n-1} A^{\dagger(n-1)}|0\rangle. \quad (\text{B7})$$

Proof: Notice that $\langle 0|A^n A^{\dagger n}|0\rangle = \langle 0|A^{n-1} [A, A^{\dagger n}]|0\rangle$ and use Lemma (B6). $\square$

Lemma (B7) shows how repeated commutators work their way into $\langle 0|A^n A^{\dagger n}|0\rangle$.

Lemma: Given $A|0\rangle = B|0\rangle = 0$ and $[[A, B^\dagger], B^\dagger] = [A, [A, B^\dagger]] = 0$, then

$$\langle 0|A^n B^{\dagger n}|0\rangle = n\langle 0|A^{n-1} B^{\dagger(n-1)}[A, B^\dagger]|0\rangle, \quad (\text{B8})$$

from which it follows that:

Lemma: Given $A|0\rangle = B|0\rangle = 0$ and $[[A, B^\dagger], B^\dagger] = [A, [A, B^\dagger]] = 0$, then

$$\langle 0|[A^n, B^{\dagger n}]|0\rangle = n!\langle 0|[A, B^\dagger]^n|0\rangle. \quad (\text{B9})$$

Note: if $A = a_f$, then $n!^{-1/2} A^{\dagger n}|0\rangle$ is an n -photon state; thus two n -photon states of this type have as their inner product the n -th power of the inner product of the corresponding 1-photon states. It follows that a unitary transform can convert an n -photon state into a tensor product of an $(n-1)$ -photon state and a 1-photon state.

Lemma: For any two operators A and B such that $[B, [A, B]] = 0$ and $n = 0, 1, 2, \dots$, we have

$$[A, B^n] = n[A, B]B^{n-1}. \quad (\text{B10})$$

(Proof follows by induction, using Lemma (B1).)

Lemma: For any two operators A and B such that $[B, [A, B]] = 0$, we have

$$[A, \exp(B)] = [A, B] \exp(B). \quad (\text{B11})$$

(Proof by expansion of exponential, using Lemma (B3).)

Lemma: Given any operators $A, B_1, \dots, B_n$,

$$\left[A, \prod_{j=1}^n B_j \right] = \sum_{\ell=1}^n \left(\prod_{j=1}^{\ell-1} B_j \right) [A, B_\ell] \left(\prod_{j=\ell+1}^n B_j \right), \quad (\text{B12})$$

with the convention that for any $m > n$ and any X_j

$$\prod_{j=m}^n X_j = 1. \quad (\text{B13})$$

1. Implications of commutation rules

Assume for the rest of this appendix the commutation rules Eqs. (2.6) and (2.7). Then we have

Lemma: For a set of frequencies $\omega, \omega_1, \dots, \omega_n$, with $n \geq 1$,

$$\left[a(\omega), \prod_{j=1}^n a^\dagger(\omega_j) \right] = \sum_{j=1}^n \delta(\omega - \omega_j) \prod_{\substack{k=1 \\ k \neq j}}^n a^\dagger(\omega_k). \quad (\text{B14})$$

Lemma: Let S_n be the permutation group on $1, \dots, n$; then

$$\langle 0 | \prod_{j=1}^m a(\omega'_j) \prod_{k=1}^n a^\dagger(\omega_k) | 0 \rangle = \delta_{mn} \sum_{\pi \in S_n} \prod_{j=1}^n \delta(\omega_j - \omega'_{\pi_j}). \quad (\text{B15})$$

From this follows

Lemma:

$$\langle 0 | (g_m^* : a^m) (h_n : a^{\dagger n}) | 0 \rangle = \delta_{mn} n! \int d\omega_1 \cdots d\omega_n g_m^*(\omega_1, \dots, \omega_n) \mathcal{S}(\omega_1, \dots, \omega_n) h_n(\omega_1, \dots, \omega_n), \quad (\text{B16})$$

where $\mathcal{S}$ is defined in (2.20). From this follows another useful fact of norms:

Lemma: If $h_n(\omega_1, \dots, \omega_n)$ is symmetric under all permutations of its arguments, then

$$\langle 0 | (h_n^* : a^n) (h_n : a^{\dagger n}) | 0 \rangle = n! \int d\omega_1 \cdots d\omega_n |h_n(\omega_1, \dots, \omega_n)|^2. \quad (\text{B17})$$

We also have the following relation that allows the calculation of some detection probabilities:

Lemma: If $[b(\omega), a^\dagger(\omega')] = 0$ and $h_n(\omega_1, \dots, \omega_n)$ is symmetric under all permutations of its arguments, then

$$\langle 0 | (h_n^* : a^k b^{n-k}) (h_n : a^{\dagger k} b^{\dagger(n-k)}) | 0 \rangle = \frac{k!(n-k)!}{n!} \langle 0 | (h_n^* : a^n) (h_n : a^{\dagger n}) | 0 \rangle. \quad (\text{B18})$$

Proof:

$$\begin{aligned} & \langle 0 | (h_n^* : a^k b^{n-k}) (h_n : a^{\dagger k} b^{\dagger(n-k)}) | 0 \rangle \\ &= \int d\omega_1 \cdots d\omega_n d\omega'_1 \cdots d\omega'_n h_n^*(\omega_1, \dots, \omega_n) h_n(\omega'_1, \dots, \omega'_n) \\ & \quad \langle 0 | a(\omega_1) \cdots a(\omega_k) b(\omega_{k+1}) \cdots b(\omega_n) a^\dagger(\omega'_1) \cdots a^\dagger(\omega'_k) b^\dagger(\omega'_{k+1}) \cdots b^\dagger(\omega'_n) | 0 \rangle. \end{aligned}$$

Because a and b work on distinct tensor-product factors, we have

$$\begin{aligned} & \langle 0 | a(\omega_1) \cdots a(\omega_k) b(\omega_{k+1}) \cdots b(\omega_n) a^\dagger(\omega'_1) \cdots a^\dagger(\omega'_k) b^\dagger(\omega'_{k+1}) \cdots b^\dagger(\omega'_n) | 0 \rangle \\ &= \langle 0 | a(\omega_1) \cdots a(\omega_k) a^\dagger(\omega'_1) \cdots a^\dagger(\omega'_k) | 0 \rangle \langle 0 | b(\omega_{k+1}) \cdots b(\omega_n) b^\dagger(\omega'_{k+1}) \cdots b^\dagger(\omega'_n) | 0 \rangle. \end{aligned}$$

The lemma then follows from the symmetry of h_n together with Lemma (B15). $\square$

Concerning broad-band coherent states, from Lemma (B14) follows:

Lemma: For $n \geq 1$,

$$a(\omega)(a_f^\dagger)^n | 0 \rangle = n f(\omega)(a_f^\dagger)^{n-1} | 0 \rangle. \quad (\text{B19})$$

Lemma: For the coherent state defined by Eq. (2.29),

$$a_g | \alpha, a_f \rangle = \int d\omega g^*(\omega) a(\omega) | \alpha, a_f \rangle = \alpha \left(\int d\omega g^*(\omega) f(\omega) \right) | \alpha, a_f \rangle. \quad (\text{B20})$$

Lemma: For $P_n(a_1, a_2)$ defined in Eq. (3.8),

$$\sum_{n=0}^{\infty} n P_n(a_1, a_2) = \int d\omega \sum_{j=1}^2 a_j^\dagger(\omega) a_j(\omega). \quad (\text{B21})$$

Proof: By the definition of Eq. (3.8), we have

$$\begin{aligned} \sum_{n=0}^{\infty} n P_n(a_1, a_2) &= \sum_{n=0}^{\infty} \sum_{k=0}^n P_k(a_1) P_{n-k}(a_2) \\ &= \sum_{k=0}^{\infty} \left(k P_k(a_1) \sum_{n=k}^{\infty} P_{n-k}(a_2) + P_k(a_1) \sum_{n=k}^{\infty} (n-k) P_{n-k}(a_2) \right). \end{aligned} \quad (\text{B22})$$

The lemma then follows from Eqs. (3.4) and (3.11).

APPENDIX C: ALGEBRA OF FREQUENCY-ENTANGLED OPERATORS

We want to evaluate expressions of the form $\langle 0 | \text{Pol}^\dagger \text{Pol} | 0 \rangle$, where Pol is a polynomial in annihilation operators. The general method of evaluation is to use commutation relations to rearrange the operators so that, in the end, nothing is left but a number. The commutation relations amount to an algebra, which we now construct for the simplest quantum models that show how polarization entanglement combines with frequency entanglement. The models

cover bi-SU(2) invariant states built up from polynomials in operators of the form $g : a_j^\dagger b_k^\dagger$. Consider some number N_a of modes derived from $a(\omega)$ and N_b of modes derived from $b(\omega)$:

$$a_j(\omega), b_k(\omega), \quad \text{for } j = 1, \dots, N_a, \text{ and } k = 1, \dots, N_b, \quad (\text{C1})$$

with

$$a_j(\omega)|0\rangle = b_k(\omega)|0\rangle = \langle 0|a_j^\dagger(\omega) = \langle 0|b_k^\dagger(\omega) = 0. \quad (\text{C2})$$

The commutation relations are

$$\begin{aligned} [a_j(\omega), a_k^\dagger(\omega')] &= \delta_{jk}\delta(\omega - \omega'), \\ [b_j(\omega), b_k^\dagger(\omega')] &= \delta_{jk}\delta(\omega - \omega'), \\ [a_j(\omega), b_k^\dagger(\omega')] &= [a_j(\omega), a_k(\omega')] = [b_j(\omega), b_k(\omega')] = 0. \end{aligned} \quad (\text{C3})$$

1. Arrow notation for frequency dependence

Let p and q denote any of these improper creation or annihilation operators. We consider operators of the form

$$p \cdot \xrightarrow{g} \cdot q \stackrel{\text{def}}{=} \int \int d\omega d\tilde{\omega} p(\omega) g(\omega, \tilde{\omega}) q(\tilde{\omega}). \quad (\text{C4})$$

Let $a^\dagger$ and $b^\dagger$ denote any of the improper creation operators and fix a square-integral function $g(\omega, \tilde{\omega})$; we are interested in the commutator algebra generated by

$$a^\dagger \cdot \xrightarrow{g} \cdot b^\dagger \quad (\text{C5})$$

and its adjoint, which is

$$(a^\dagger \cdot \xrightarrow{g} \cdot b^\dagger)^\dagger = b \cdot \xleftarrow{g^*} \cdot a = a \cdot \xrightarrow{g^*} \cdot b. \quad (\text{C6})$$

We now develop this arrow notation. For any function of two variables $g(x_1, x_2)$ that enters as a factor in an integrand, we write g as $\xrightarrow{g}$ if the second variable is identified with a variable in a following factor or if the first variable is identified with a variable in a preceding factor; we write $\xleftarrow{g}$ if the first variable is identified with a variable in a following factor

or if the second variable is identified with a variable in a preceding factor. This makes it easy to express compound convolutions that will occur in commutators, such as $G_I(x_1, x_2) = \int \int dx dx' f(x_1, x) g(x', x) h(x', x_2)$ and $G_{II}(x_1, x_2) = \int \int dx dx' f(x_1, x) g(x, x') h(x', x_2)$; because the order is different in the middle factor, G_I and G_{II} are distinct. Writing a “.” for integration, we then diagram

$$\begin{aligned} G_I(x_1, x_2) & \text{ as } x_1 \xrightarrow{f} \cdot \xleftarrow{g} \cdot \xrightarrow{h} x_2, \\ G_{II}(x_1, x_2) & \text{ as } x_1 \xrightarrow{f} \cdot \xrightarrow{g} \cdot \xrightarrow{h} x_2. \end{aligned} \quad (C7)$$

Altogether there are eight such functions, corresponding to the eight ways to orient a sequence of three arrows.

A compound function such as G_I can itself enter another compound. If G is defined by an arrow diagram with the above procedure, then $\xrightarrow{G}$ is obtained immediately as that diagram while $\xleftarrow{G}$ is obtained by left-right reflection of the diagram, as in

$$\begin{aligned} \xrightarrow{G_I} &= \xrightarrow{f} \cdot \xleftarrow{g} \cdot \xrightarrow{h}, \\ \xleftarrow{G_I} &= \xleftarrow{h} \cdot \xrightarrow{g} \cdot \xleftarrow{f}. \end{aligned} \quad (C8)$$

We abbreviate repetitive patterns by an exponent; for example

$$\xrightarrow{g} \cdot \xleftarrow{h} \cdot \xrightarrow{g} \cdot \xleftarrow{h} \cdot \xrightarrow{g} = \left(\xrightarrow{g} \cdot \xleftarrow{h} \right)^2 \cdot \xrightarrow{g}. \quad (C9)$$

We define an operation ‘Loop’ that produces a number from a string of arrows by joining the two terminal points; for example

$$\text{Loop}\left(\xrightarrow{g} \cdot \xleftarrow{h}\right) = (g^*, h) = \int \int d\omega d\tilde{\omega} g(\omega, \tilde{\omega}) h(\omega, \tilde{\omega}). \quad (C10)$$

Lemma:

$$\xleftarrow{h} \cdot \left(\xrightarrow{g} \cdot \xleftarrow{h} \right)^n \cdot \xrightarrow{g} = \left(\xleftarrow{h} \cdot \xrightarrow{g} \right)^{n+1}. \quad (C11)$$

Lemma: With these arrow rules, if $[p, q] = 0$, then

$$p \cdot \xrightarrow{g} \cdot q = q \cdot \xleftarrow{g} \cdot p. \quad (C12)$$

2. Algebra rules

Equations (C3) imply a commutator algebra generated by

$$a_j \cdot \xrightarrow{g^*} \cdot b_k \quad \text{and} \quad a_j^\dagger \cdot \xrightarrow{g} \cdot b_k^\dagger. \quad (\text{C13})$$

The commutator of these, along with commutators of commutators, etc., generate new frequency functions. Regardless of the frequency function g , the operator $a_j \cdot \xrightarrow{g} \cdot b_k$ acting to the right on the vacuum state annihilates the state. We will speak of such an operator, regardless of its frequency function, as being of *annihilation type*. In addition to the creation and annihilation types that we start with, the commutation relations engender two more types, one type has the form $a_j^\dagger \cdot \rightarrow \cdot a_k$ or $b_j^\dagger \cdot \rightarrow \cdot b_k$, the other type is just a number. The point is to evaluate expressions of the form $\langle 0 | \text{Pol}^\dagger \text{Pol} | 0 \rangle$ by using the commutator algebra to transform this to a form $\langle 0 | x | 0 \rangle$, where x is just a number, extracted in the last step from the normalization relation $\langle 0 | 0 \rangle = 1$.

The commutation relations among all these types are defined by the following and their hermitian conjugates:

$$\begin{aligned} [a_j \cdot \xrightarrow{g} \cdot b_k, a_\ell^\dagger \cdot \xrightarrow{h} \cdot b_m^\dagger] &= \delta_{km} a_\ell^\dagger \cdot \xrightarrow{h} \cdot \xleftarrow{g} \cdot a_j + \delta_{j\ell} b_m^\dagger \cdot \xleftarrow{h} \cdot \xrightarrow{g} \cdot b_k \\ &\quad + \delta_{j\ell} \delta_{km} \text{Loop} \left(\xleftarrow{h} \cdot \xrightarrow{g} \right), \end{aligned} \quad (\text{C14})$$

$$[a_j^\dagger \cdot \xrightarrow{g} \cdot a_k, a_\ell^\dagger \cdot \xrightarrow{h} \cdot b_m^\dagger] = \delta_{k\ell} a_j^\dagger \cdot \xrightarrow{g} \cdot \xrightarrow{h} \cdot b_m^\dagger, \quad (\text{C15})$$

$$[a_j^\dagger \cdot \xrightarrow{g} \cdot a_k, a_\ell^\dagger \cdot \xrightarrow{h} \cdot a_m^\dagger] = \delta_{k\ell} a_j^\dagger \cdot \xrightarrow{g} \cdot \xrightarrow{h} \cdot a_m - \delta_{jm} a_\ell^\dagger \cdot \xrightarrow{h} \cdot \xrightarrow{g} \cdot a_k, \quad (\text{C16})$$

$$[b_j^\dagger \cdot \xrightarrow{g} \cdot b_k, a_\ell^\dagger \cdot \xrightarrow{h} \cdot b_m^\dagger] = \delta_{km} a_\ell^\dagger \cdot \xrightarrow{h} \cdot \xleftarrow{g} \cdot b_j^\dagger, \quad (\text{C17})$$

$$[b_j^\dagger \cdot \xrightarrow{g} \cdot b_k, b_\ell^\dagger \cdot \xrightarrow{h} \cdot b_m^\dagger] = \delta_{k\ell} b_j^\dagger \cdot \xrightarrow{g} \cdot \xrightarrow{h} \cdot b_m - \delta_{jm} b_\ell^\dagger \cdot \xrightarrow{h} \cdot \xrightarrow{g} \cdot b_k. \quad (\text{C18})$$

These relations hold for any integrable functions $g(\omega, \omega')$ and $h(\omega, \omega')$.

3. Subalgebra for fixed g

For constructing examples, we will use a subalgebra in which a chosen $g(\omega, \omega')$ plays a distinguished role. Given any such g , define for $n = 1, 2, \dots$,

$$\begin{aligned}\overrightarrow{g_n} &= \left(\overrightarrow{g} \cdot \overleftarrow{g^*} \right)^{n-1} \cdot \overrightarrow{g}, \\ \overleftarrow{g_n} &= \overleftarrow{g} \cdot \left(\overrightarrow{g^*} \cdot \overleftarrow{g} \right)^{n-1}, \\ \check{G}_n &= \left(\overrightarrow{g} \cdot \overleftarrow{g^*} \right)^n, \\ \widehat{G}_n &= \left(\overleftarrow{g} \cdot \overrightarrow{g^*} \right)^n.\end{aligned}\tag{C19}$$

By writing out a few arrow expressions, one shows for positive integers r and s

$$\overrightarrow{g_s} \cdot \overleftarrow{g_r^*} = \left(\overrightarrow{g} \cdot \overleftarrow{g^*} \right)^{r+s-1} = \check{G}_{r+s-1},\tag{C20}$$

$$\overleftarrow{g_s} \cdot \overrightarrow{g_r^*} = \left(\overleftarrow{g} \cdot \overrightarrow{g^*} \right)^{r+s-1},\tag{C21}$$

$$\check{G}_r \cdot \overrightarrow{g_s} = \overrightarrow{g_{r+s}},\tag{C22}$$

$$\overrightarrow{g_s} \cdot \widehat{G}_r = \overrightarrow{g_{r+s}},\tag{C23}$$

$$\check{G}_r \cdot \check{G}_s = \check{G}_{r+s},\tag{C24}$$

$$\widehat{G}_r \cdot \widehat{G}_s = \widehat{G}_{r+s},\tag{C25}$$

$$\overrightarrow{G_n} = \overleftarrow{G_n^*},\tag{C26}$$

$$\check{G}_n = \overleftarrow{G_n^*}.\tag{C27}$$

With these and the definition in Eq. (C19), we find

$$\begin{aligned}\left[a_j \cdot \overrightarrow{g_r^*} \cdot b_k, a_\ell^\dagger \cdot \overrightarrow{g_s} \cdot b_m^\dagger \right] &= \delta_{km} a_\ell^\dagger \cdot \check{G}_{r+s-1} \cdot a_j + \delta_{j\ell} b_m^\dagger \cdot \widehat{G}_{r+s-1} \cdot b_k \\ &\quad + \delta_{j\ell} \delta_{km} \text{Loop}(\widehat{G}_{r+s-1}),\end{aligned}\tag{C28}$$

$$\left[a_j^\dagger \cdot \check{G}_r \cdot a_k, a_\ell^\dagger \cdot \overrightarrow{g_s} \cdot b_m^\dagger \right] = \delta_{k\ell} a_j^\dagger \cdot \overrightarrow{g_{r+s}} \cdot b_m^\dagger,\tag{C29}$$

$$\left[a_j^\dagger \cdot \check{G}_r \cdot a_k, a_\ell^\dagger \cdot \check{G}_s \cdot a_m \right] = \delta_{k\ell} a_j^\dagger \cdot \check{G}_{r+s} \cdot a_m - \delta_{jm} a_\ell^\dagger \cdot \check{G}_{r+s} \cdot a_k,\tag{C30}$$

$$\left[b_j^\dagger \cdot \widehat{G}_r \cdot b_k, a_\ell^\dagger \cdot \overrightarrow{g_s} \cdot b_m^\dagger \right] = \delta_{km} a_\ell^\dagger \cdot \overrightarrow{g_{r+s}} \cdot b_j^\dagger,\tag{C31}$$

$$\left[b_j^\dagger \cdot \xrightarrow{\widehat{G}_r} \cdot b_k, b_\ell^\dagger \cdot \xrightarrow{\widehat{G}_s} \cdot b_m \right] = \delta_{k\ell} b_j^\dagger \cdot \xrightarrow{\widehat{G}_{r+s}} \cdot b_m - \delta_{jm} b_\ell^\dagger \cdot \xrightarrow{\widehat{G}_{r+s}} \cdot b_k. \quad (\text{C32})$$

4. Commutators of powers of operators

To evaluate powers of operators, we shall need some repeated commutators.

Lemma: For any positive integers r, s, q ,

$$\left[\left[a_j \cdot \xrightarrow{g_r^*} \cdot b_k, a_\ell^\dagger \cdot \xrightarrow{g_s} \cdot b_m^\dagger \right], a_\ell^\dagger \cdot \xrightarrow{g_q} \cdot b_m^\dagger \right] = 2\delta_{j\ell}\delta_{km} a_\ell^\dagger \cdot \xrightarrow{g_{q+r+s-1}} \cdot b_m^\dagger. \quad (\text{C33})$$

It is worth noticing that this double commutator is of *creation type*, and thus commutes with all other operators of that type. The commutation relations also imply

Lemma: Regardless of what functions decorate the arrows,

$$[[a \cdot \rightarrow \cdot b_j, a^\dagger \cdot \rightarrow \cdot b_k^\dagger], a^\dagger \cdot \rightarrow \cdot b_k^\dagger] = 0, \quad \text{if } j \neq k. \quad (\text{C34})$$

In particular the operators $a_j \cdot \xrightarrow{g^*} \cdot b_k$ and $a_j^\dagger \cdot \xrightarrow{g} \cdot b_k^\dagger$ above fulfill the conditions for this lemma.

Proposition: Write (ab_j) for $a \cdot \xrightarrow{g^*} \cdot b_j$ and for non-negative integers $n_1, n_2, \dots, n_K$, let $n = \sum_{j=1}^K n_j$; then

$$\langle 0 | \left(\prod_{j=1}^K (ab_j)^{n_j} \right) \left(\prod_{j=1}^K (ab_j)^\dagger{}^{n_j} \right) | 0 \rangle = \frac{n_1! n_2! \cdots n_K!}{n!} \langle 0 | (ab_1)^n (ab_1)^\dagger{}^n | 0 \rangle. \quad (\text{C35})$$

Proof: The proof employs the symmetry operator of Eq. (2.20). The left side of the equation is the inner product of a vector $|\phi\rangle$ with itself, where

$$\begin{aligned} |\phi\rangle &= h_{2n} : \text{Pol}^\dagger | 0 \rangle \\ &= \int d\omega_1 d\tilde{\omega}_1 \cdots d\omega_n d\tilde{\omega}_n h_{2n}(\omega_1, \tilde{\omega}_1, \dots, \omega_n, \tilde{\omega}_n) \text{Pol}^\dagger | 0 \rangle, \end{aligned}$$

with

$$h_{2n}(\omega_1, \tilde{\omega}_1, \dots, \omega_n, \tilde{\omega}_n) = g(\omega_1, \tilde{\omega}_1) \cdots g(\omega_n, \tilde{\omega}_n) \quad (\text{C36})$$

and

$$\text{Pol}^\dagger = \left(\prod_{j=1}^{n_1} a^\dagger(\omega_j) b_1^\dagger(\tilde{\omega}_j) \right) \cdots \left(\prod_{j=n-n_K+1}^n a^\dagger(\omega_j) b_K^\dagger(\tilde{\omega}_j) \right). \quad (\text{C37})$$

Because of the commutativity relations, the integral is unchanged under certain permutations of the arguments of h_{2n} . Interchanging the operators $a^\dagger(\omega_j)$ among themselves yields

$$|\phi\rangle = (\mathcal{S}(\omega_1, \dots, \omega_n) h_{2n}) : \text{Pol}^\dagger |0\rangle. \quad (\text{C38})$$

In addition, letting $\vec{\omega}_j = (\omega_j, \tilde{\omega}_j)$, we have

$$|\phi\rangle = (\mathcal{S}(\vec{\omega}_1, \dots, \vec{\omega}_n) h_{2n}) : \text{Pol}^\dagger |0\rangle. \quad (\text{C39})$$

These two symmetries for h_{2n} and its product form defined in Eq. (C36) imply a third symmetry:

$$|\phi\rangle = (\mathcal{S}(\tilde{\omega}_1, \dots, \tilde{\omega}_n) h_{2n}) : \text{Pol}^\dagger |0\rangle. \quad (\text{C40})$$

From this symmetry and Lemma (B15) the proposition follows. $\square$

This generalizes Lemma (B18).

We shall need to refer to a function

$$\Xi_g(n) \stackrel{\text{def}}{=} \frac{1}{n!} \langle 0 | (ab)^n (ab)^\dagger | 0 \rangle. \quad (\text{C41})$$

This function is independent of the choice of operators $a(\omega)$ and $b(\omega)$ as long as each operator satisfies the commutation relations Eqs. (2.6), (2.7) and the two operators are mutually orthogonal.

Proposition: Write (ab) for $a \cdot \xrightarrow{g^*} \cdot b$. Then

$$\begin{aligned} \Xi_g(n) &\stackrel{\text{def}}{=} \frac{1}{n!} \langle 0 | (ab)^n (ab)^\dagger | 0 \rangle \\ &= \sum_{\substack{\nu_1, \dots, \nu_n=0 \\ \sum k \nu_k = n}}^n \frac{n!}{1^{\nu_1} \nu_1! 2^{\nu_2} \nu_2! \dots n^{\nu_n} \nu_n!} \prod_{j=1}^n [\text{Loop}(\hat{G}_j)]^{\nu_j}, \end{aligned} \quad (\text{C42})$$

where the ν_k are restricted as indicated.

Proof: From symmetry considerations and Lemma (B15) we get

$$\begin{aligned} \frac{1}{n!} \langle 0 | (ab)^n (ab)^\dagger | 0 \rangle &= \frac{1}{n!} \int d\omega_1 d\tilde{\omega}_1 \dots d\omega_n d\tilde{\omega}_n d\omega'_1 d\tilde{\omega}'_1 \dots d\omega'_n d\tilde{\omega}'_n \\ &\quad [g(\omega_1, \tilde{\omega}_1) \dots g(\omega_n, \tilde{\omega}_n)] [g^*(\omega'_1, \tilde{\omega}'_1) \dots g^*(\omega'_n, \tilde{\omega}'_n)] \\ &\quad \times \left(\sum_{\pi \in S_n} \prod_{j=1}^n \delta(\omega_j - \omega'_{\pi j}) \right) \left(\sum_{\pi \in S_n} \prod_{j=1}^n \delta(\tilde{\omega}_j - \tilde{\omega}'_{\pi j}) \right). \end{aligned} \quad (\text{C43})$$

By virtue of Eq. (C39), any permutation of the variables $\tilde{\omega}'_{\pi j}$ is compensated out by a corresponding permutation of the variables $\omega'_{\pi j}$, which implies

$$\begin{aligned}
\frac{1}{n!} \langle 0 | (ab)^n (ab)^{\dagger n} | 0 \rangle &= \int d\omega_1 d\tilde{\omega}_1 \cdots d\omega_n d\tilde{\omega}_n d\omega'_1 \cdots d\omega'_n [g(\omega_1, \tilde{\omega}_1) \cdots g(\omega_n, \tilde{\omega}_n)] \\
&\quad \times [g^*(\omega'_1, \tilde{\omega}_1) \cdots g^*(\omega'_n, \tilde{\omega}_n)] \left(\sum_{\pi \in S_n} \prod_{j=1}^n \delta(\omega_j - \omega'_{\pi j}) \right) \\
&= n! \int d\omega_1 d\tilde{\omega}_1 \cdots d\omega_n d\tilde{\omega}_n |\mathcal{S}(\omega_1, \dots, \omega_n) g(\omega_1, \tilde{\omega}_1) \cdots g(\omega_n, \tilde{\omega}_n)|^2.
\end{aligned} \tag{C44}$$

The effect of each of these remaining permutations is to generate a product of integrals, each of convolutions of g 's with matching convolutions of g^* 's, according to the cycle structure of the permutation group S_n . The convolutions generated by a permutation are those that correspond to the cycles of its conjugacy class. Each conjugacy class is characterized by some $[\nu_1, \dots, \nu_n]$ where ν_1 is the number of one-cycles, ν_2 is the number of two-cycles, etc. (with $\sum_{k=1}^n k\nu_k = n$) [17]. The number of permutations in a conjugacy class is just that stated in the Proposition [17].

□

Examples are

$$\begin{aligned}
\Xi_g(0) &= 1, \\
\Xi_g(1) &= \text{Loop}(\hat{G}_1), \\
\Xi_g(2) &= [\text{Loop}(\hat{G}_1)]^2 + \text{Loop}(\hat{G}_2), \\
\Xi_g(3) &= [\text{Loop}(\hat{G}_1)]^3 + 3[\text{Loop}(\hat{G}_1)][\text{Loop}(\hat{G}_2)] + 2\text{Loop}(\hat{G}_3).
\end{aligned} \tag{C45}$$

As a check on the Proposition, these examples can also be demonstrated by repeated use of Eq. (B7) along with the commutation relations Eqs. (C28)–(C32).

We will need to deal with partial traces, as defined in Sec. 2, in particular we need

$$\begin{aligned}
\text{Tr}_a[(ab)^{\dagger n} | 0 \rangle \langle 0 | (ab)^n] &= \int d\tilde{\omega} d\tilde{\omega}' \\
&\quad \left[\int d\omega d\omega' g(\omega, \tilde{\omega}) g^*(\omega', \tilde{\omega}') \langle 0_a | a^n(\omega') a^{\dagger n}(\omega) | 0_a \rangle \right] b^{\dagger n}(\tilde{\omega}) | 0_b \rangle \langle 0_b | b^n(\tilde{\omega}') \\
&= n! \int d\tilde{\omega} d\tilde{\omega}' \left[\int d\omega g(\omega, \tilde{\omega}) \mathcal{S}(\omega) g^*(\omega, \tilde{\omega}') \right] b^{\dagger n}(\tilde{\omega}) | 0_b \rangle \langle 0_b | b^n(\tilde{\omega}'),
\end{aligned} \tag{C46}$$

where we have used the compact notation defined in Sec. 2, with $\mathbf{g}(\boldsymbol{\omega}, \tilde{\boldsymbol{\omega}}) \stackrel{\text{def}}{=} g(\omega_1, \tilde{\omega}_1) \cdots g(\omega_n, \tilde{\omega}_n)$, and the second equality invokes Lemma (B15). Because of symmetry of the b operators under permutations of their arguments, this simplifies to

$$\text{Tr}_a[(ab)^{\dagger n}|0\rangle\langle 0|(ab)^n] = n! \int d\tilde{\boldsymbol{\omega}} d\tilde{\boldsymbol{\omega}}' \left[\int d\boldsymbol{\omega} \mathbf{g}(\boldsymbol{\omega}, \tilde{\boldsymbol{\omega}}) \mathbf{g}^*(\boldsymbol{\omega}, \tilde{\boldsymbol{\omega}}') \right] b^{\dagger n}(\tilde{\boldsymbol{\omega}})|0_b\rangle\langle 0_b|b^n(\tilde{\boldsymbol{\omega}}'). \quad (\text{C47})$$

Writing out the compact notion, we note that the inner integral above is

$$\begin{aligned} \int d\boldsymbol{\omega} \mathbf{g}(\boldsymbol{\omega}, \tilde{\boldsymbol{\omega}}) \mathbf{g}^*(\boldsymbol{\omega}, \tilde{\boldsymbol{\omega}}') &= \prod_{j=1}^n \left(\int d\omega g(\omega, \tilde{\omega}_j) g^*(\omega, \tilde{\omega}'_j) \right) \\ &= \prod_{j=1}^n \left(\tilde{\omega}_j \xleftarrow{g} \cdot \xrightarrow{g^*} \tilde{\omega}'_j \right). \end{aligned} \quad (\text{C48})$$

As a check, we note that the trace over the b -mode of Eq. (C47) results in Proposition (C42), as it should.

5. Examples of frequency functions

We consider a family of functions $g_\zeta(\omega, \tilde{\omega})$ and show two limiting cases. For any real-valued functions $\phi(\omega)$ and $\tilde{\phi}(\tilde{\omega})$ and positive real parameters σ and $\tilde{\sigma}$, let

$$g_\zeta(\omega, \tilde{\omega}) = \frac{1}{\sqrt{\sigma\tilde{\sigma}}} e^{i\phi(\omega)} e^{i\tilde{\phi}(\tilde{\omega})} F\left(\zeta; \frac{\omega - \omega_0}{\sigma}, \frac{\tilde{\omega} - \tilde{\omega}_0}{\tilde{\sigma}}\right), \quad (\text{C49})$$

where we define

$$\begin{aligned} F(\zeta; x, y) &\stackrel{\text{def}}{=} \sqrt{\frac{2}{\pi}} \exp \left\{ -\frac{1}{2} \left[\left(\sqrt{\zeta^2 + 1} + \zeta \right) (x + y)^2 + \left(\sqrt{\zeta^2 + 1} - \zeta \right) (x - y)^2 \right] \right\} \\ &= \sqrt{\frac{2}{\pi}} \exp \left\{ -\left[\sqrt{\zeta^2 + 1} (x^2 + y^2) + 2\zeta xy \right] \right\}; \end{aligned} \quad (\text{C50})$$

regardless of the value of ζ ,

$$\int_{-\infty}^{\infty} dx dy |F(\zeta; x, y)|^2 = 1. \quad (\text{C51})$$

Thus for any choice of center frequencies ω_0 and $\tilde{\omega}_0$, bandwidth parameters σ and $\tilde{\sigma}$, and phase functions $\phi(\omega)$ and $\tilde{\phi}(\tilde{\omega})$, we get a family of g_ζ 's.

By changing integration variables, one shows

$$\text{Loop}\left[\left(\overrightarrow{g_\zeta} \cdot \overleftarrow{g_\zeta^*}\right)^n\right] = \text{Loop}\left[\left(\overrightarrow{F} \cdot \overleftarrow{F^*}\right)^n\right], \quad (\text{C52})$$

and similarly for the convolution of g_ζ 's

$$\omega\left(\overrightarrow{g_\zeta} \cdot \overleftarrow{g_\zeta^*}\right)^n \cdot \overrightarrow{g_\zeta} \tilde{\omega} = \frac{1}{\sqrt{\sigma\tilde{\sigma}}} e^{i\phi(\omega)} e^{i\tilde{\phi}(\tilde{\omega})} \left(\frac{\omega - \omega_0}{\sigma} \left(\overrightarrow{F} \cdot \overleftarrow{F^*}\right)^n \cdot \overrightarrow{F} \frac{\tilde{\omega} - \tilde{\omega}_0}{\tilde{\sigma}}\right). \quad (\text{C53})$$

It remains to compute the convolution integrals for F . Although $g_\zeta(\omega, \tilde{\omega})$ need be neither real-valued nor symmetric in ω and $\tilde{\omega}$, the function $F(\zeta; x, y)$ is real and symmetric, implying

$$\overrightarrow{F} = \overleftarrow{F} = \overrightarrow{F^*} = \overleftarrow{F^*}. \quad (\text{C54})$$

For this reason arrow expressions built up from convolutions of factors of F are invariant under any number of reverses of arrow directions; to emphasize this indifference to arrow direction in F (but not g_ζ), we write

$$\overleftrightarrow{F}. \quad (\text{C55})$$

To compute the convolution integrals for F , consider a sequence of ζ_j . Abbreviating $F(\zeta_j; \cdot, \cdot)$ by F_j and $\sqrt{\zeta_j^2 + 1}$ by c_j , we have

$$\begin{aligned} x \overleftrightarrow{F_j} \cdot \overleftrightarrow{F_k} y &\stackrel{\text{def}}{=} \frac{2}{\pi} \int dz \exp\{-[c_j(x^2 + z^2) + c_k(z^2 + y^2) + 2\zeta_j xz + 2\zeta_k zy]\} \\ &= \sqrt{\frac{2}{c_j + c_k}} \sqrt{\frac{2}{\pi}} \exp\left\{-\left(\left[-\frac{\zeta_j \zeta_k}{c_j + c_k}\right]^2 + 1\right)^{1/2} (x^2 + y^2) - \frac{2\zeta_j \zeta_k}{c_j + c_k} xy\right\} \\ &= \sqrt{\frac{2}{c_j + c_k}} F\left(-\frac{\zeta_j \zeta_k}{c_j + c_k}; x, y\right). \end{aligned} \quad (\text{C56})$$

Setting $y = x$ and integrating yield

$$(\forall j) \quad \text{Loop}\left(\overleftrightarrow{F_j} \cdot \overleftrightarrow{F_j}\right) = 1. \quad (\text{C57})$$

From this and Eqs. (C50) and (C56) follows the

Lemma:

$$x\left(\overleftrightarrow{F(\zeta)}\right)^n y = \sqrt{\kappa(\zeta, n)} F(\zeta_n; x, y), \quad (\text{C58})$$

where we have written $F(\zeta)$ as an abbreviation for $F(\zeta; \cdot, \cdot)$ and

$$\kappa(\zeta, 1) = 1, \quad (\text{C59})$$

$$\zeta_1 = \zeta, \quad (\text{C60})$$

$$\zeta_{n+1} = -\frac{\zeta_1 \zeta_n}{\sqrt{\zeta_1^2 + 1} + \sqrt{\zeta_n^2 + 1}}, \quad (\text{C61})$$

$$\kappa(\zeta, n+1) = \frac{2}{\sqrt{\zeta_1^2 + 1} + \sqrt{\zeta_n^2 + 1}}. \quad (\text{C62})$$

From the lemma and these equations we find

$$\begin{aligned} \text{Loop}\left(\overrightarrow{\check{G}_{\zeta^n}}\right) &\equiv \text{Loop}\left[\left(\overrightarrow{g_\zeta} \cdot \overleftarrow{g_\zeta^*}\right)^n\right] \\ &= \text{Loop}\left[\left(\overleftrightarrow{F(\zeta)} \cdot \overleftrightarrow{F(\zeta)}\right)^n\right] \\ &= \text{Loop}\left[\left(\overleftrightarrow{F(\zeta)}\right)^n \cdot \left(\overleftrightarrow{F(\zeta)}\right)^n\right] \\ &= \kappa(\zeta, n), \end{aligned} \quad (\text{C63})$$

with $\kappa(\zeta, n)$ as defined in (C62). Similarly this and Eq. (C19) yield

$$\text{Loop}\left(\overrightarrow{g_{\zeta^n}} \cdot \overleftarrow{g_{\zeta^n}^*}\right) = \text{Loop}\left(\overrightarrow{\check{G}_{\zeta, 2n-1}}\right) = \kappa(\zeta, 2n-1). \quad (\text{C64})$$

Note that Eq. (C62) implies

$$(\forall n \geq 2) \quad \kappa(\zeta, n) \leq \frac{2}{|\zeta|}. \quad (\text{C65})$$

For more efficient calculation, define $R(\zeta, n)$ for $n \geq 2$ by

$$\kappa(\zeta, n) = \frac{R(\zeta, n)}{\sqrt{\zeta^2 + 1}}. \quad (\text{C66})$$

From Eqs. (C59) and (C62), it follows that $R(\zeta, n)$ is a rational function of ζ satisfying the following recursion relation

Lemma:

$$R(\zeta, 2) = 1, \quad (\text{C67})$$

$$(\forall n \geq 2) \quad R(\zeta, n+1) = \left(1 - \frac{\zeta^2}{4(\zeta^2 + 1)} R(\zeta, n)\right)^{-1}. \quad (\text{C68})$$

From Lemma (C58) and Eq. (C53) one also finds

$$\omega \xrightarrow{g_{\zeta n}} \tilde{\omega} = k_{2n+1} \frac{1}{\sqrt{\sigma\tilde{\sigma}}} e^{i\phi(\omega)} e^{i\tilde{\phi}(\tilde{\omega})} F\left(\zeta_{2n+1}; \frac{\omega - \omega_0}{\sigma}, \frac{\tilde{\omega} - \tilde{\omega}_0}{\tilde{\sigma}}\right), \quad (\text{C69})$$

$$\omega_1 \xrightarrow{\check{G}_{\zeta n}} \omega_2 = \sigma^{-1} k_{2n} \exp\{i[\phi(\omega_1) - \phi(\omega_2)]\} F\left(\zeta_{2n}; \frac{\omega_1 - \omega_0}{\sigma}, \frac{\omega_2 - \omega_0}{\sigma}\right), \quad (\text{C70})$$

$$\tilde{\omega}_1 \xrightarrow{\hat{G}_{\zeta n}} \tilde{\omega}_2 = \tilde{\sigma}^{-1} k_{2n} \exp\{i[\tilde{\phi}(\tilde{\omega}_1) - \tilde{\phi}(\tilde{\omega}_2)]\} F\left(\zeta_{2n}; \frac{\tilde{\omega}_1 - \tilde{\omega}_0}{\tilde{\sigma}}, \frac{\tilde{\omega}_2 - \tilde{\omega}_0}{\tilde{\sigma}}\right). \quad (\text{C71})$$

6. Limiting cases

Case I. No frequency entanglement: $g_{\text{I}}(\omega, \tilde{\omega}) = f(\omega)h(\tilde{\omega})$, normalized so that $\iint d\omega d\tilde{\omega} |g(\omega, \tilde{\omega})|^2 = \int d\omega |f(\omega)|^2 = \int d\tilde{\omega} |h(\tilde{\omega})|^2 = 1$. In this case, one skips the fancy commutation relations because the operators all factor; we find

Lemma:

$$\Xi_{\text{I}}(n) \stackrel{\text{def}}{=} \frac{1}{n!} \langle 0 | \left(a \cdot \xrightarrow{g_{\text{I}}} \cdot b \right)^n \left(a^\dagger \cdot \xrightarrow{g_{\text{I}}} \cdot b^\dagger \right)^n | 0 \rangle = n!, \quad (\text{C72})$$

which follows from the discussion of broad-band coherent states in Sec. 2 C.

Case II. Limit as $\zeta \rightarrow \pm\infty$. It makes no sense to ask for the limit of g_ζ ; however, we explore large values of $|\zeta|$ by looking at the limit of the commutation relations. From Eqs. (C62) and (C64) we see for this limit

$$(\text{for } n \geq 2) \quad \lim_{\zeta \rightarrow \pm\infty} k_n = \lim_{\zeta \rightarrow \pm\infty} \text{Loop}\left(\xrightarrow{\check{G}_{\text{II}n}}\right) = \lim_{\zeta \rightarrow \pm\infty} \text{Loop}\left(\xrightarrow{g_{\zeta n}} \cdot \xleftarrow{g_{\zeta n}^*}\right) = 0, \quad (\text{C73})$$

resulting in specializing the commutation Eqs. (C28)–(C32), for sufficiently large $|\zeta|$, to

$$\begin{aligned} & \left[a_j \cdot \xrightarrow{g^*} \cdot b_k, a_\ell^\dagger \cdot \xrightarrow{g} \cdot b_m^\dagger \right] \\ &= \delta_{km} a_\ell^\dagger \cdot \xrightarrow{\check{G}_1} \cdot a_j + \delta_{j\ell} b_m^\dagger \cdot \xrightarrow{\hat{G}_1} \cdot b_k + \delta_{j\ell} \delta_{km}, \end{aligned} \quad (\text{C74})$$

$$\lim_{\zeta \rightarrow \pm\infty} \left[a_j^\dagger \cdot \xrightarrow{\check{G}_1} \cdot a_k, a_\ell^\dagger \cdot \xrightarrow{g} \cdot b_m^\dagger \right] = 0, \quad (\text{C75})$$

$$\lim_{\zeta \rightarrow \pm\infty} \left[a_j^\dagger \cdot \xrightarrow{\check{G}_1} \cdot a_k, a_\ell^\dagger \cdot \xrightarrow{\check{G}_1} \cdot a_m \right] = 0, \quad (\text{C76})$$

$$\lim_{\zeta \rightarrow \pm\infty} \left[b_j^\dagger \cdot \xrightarrow{\hat{G}_1} \cdot b_k, a_\ell^\dagger \cdot \xrightarrow{g} \cdot b_m^\dagger \right] = 0, \quad (\text{C77})$$

$$\lim_{\zeta \rightarrow \pm\infty} \left[b_j^\dagger \cdot \xrightarrow{\hat{G}_1} \cdot b_k, b_\ell^\dagger \cdot \xrightarrow{\hat{G}_1} \cdot b_m \right] = 0. \quad (\text{C78})$$

In this case, the double commutator $\left[\left[a_j \cdot \xrightarrow{g^*} \cdot b_k, a_\ell^\dagger \cdot \xrightarrow{g} \cdot b_m^\dagger \right], a_\ell^\dagger \cdot \xrightarrow{g} \cdot b_m^\dagger \right]$ is effectively zero, so that Lemma (B6) applies.

From Lemma (B9) and Eqs. (C74)–(C78) follows the corresponding rule for evaluating Case-II operator products:

Lemma:

$$\Xi_{\text{II}}(n) \stackrel{\text{def}}{=} \lim_{\zeta \rightarrow \pm\infty} \frac{1}{n!} \langle 0 | \left(a \cdot \xrightarrow{g^*} \cdot b \right)^n \left(a^\dagger \cdot \xrightarrow{g} \cdot b^\dagger \right)^n | 0 \rangle = 1. \quad (\text{C79})$$

APPENDIX D: FOURIER TRANSFORMS IN SPACE AND TIME

Let $f(x, t)$ be any operator-valued function for which Fourier transforms make sense, and define the Fourier transform pair:

$$\bar{f}(\omega, k) = (2\pi)^{-1} \int_{-\infty}^{\infty} dt \int_{-\infty}^{\infty} dx f(x, t) e^{i(\omega t + kx)}, \quad (\text{D1})$$

$$f(x, t) = (2\pi)^{-1} \int_{-\infty}^{\infty} d\omega \int_{-\infty}^{\infty} dk \bar{f}(\omega, k) e^{-i(\omega t + kx)}. \quad (\text{D2})$$

On taking the adjoint of these equations, one sees that:

Lemma: The Fourier transform of $f^\dagger(x, t)$ is related to the adjoint of the transform of $f(x, t)$ by

$$\bar{f}^\dagger(-\omega, -k) = (\bar{f}(\omega, k))^\dagger. \quad (\text{D3})$$

Lemma: If $f(x, t) = f^\dagger(x, t)$, then

$$\bar{f}(-\omega, -k) = (\bar{f}(\omega, k))^\dagger, \quad (\text{D4})$$

so that the Fourier transform of a hermitian operator function is specified for the whole (ω, k) -plane once it is specified for any half-plane touching the origin. In particular Eq. (D2) can be replaced by

$$f(x, t) = (2\pi)^{-1} \int_{-\infty}^{\infty} d\omega \int_0^{\infty} dk \left(\bar{f}(\omega, k) e^{-i(\omega t + kx)} + \bar{f}^\dagger(\omega, k) e^{i(\omega t + kx)} \right), \quad (\text{D5})$$

where the integrand is integrated over the half-plane $k > 0$; alternatively $f(x, t)$ can be expressed by the same integrand integrated over the half-plane defined by $\omega > 0$. More generally,

the region of integration needs to be obtained from the region excluded by reflection through the origin; thus the region of integration need not be aligned with the axes and need not have a straight boundary.

Lemma: If $\overline{f}(\omega, k) = \overline{f}^\dagger(\omega, k)$, then

$$\overline{f}(-\omega, -k) = (\overline{f}(\omega, k))^\dagger. \quad (\text{D6})$$

Now consider the form of a Fourier transform of any solution to the wave equation

$$(\partial_x^2 - \partial_t^2)g(x, t) = 0; \quad (\text{D7})$$

this equation has as its general solution

$$g(x, t) = g_+(t - x) + g_+(t + x), \quad (\text{D8})$$

so that the transform of g has the form

$$\overline{g}(\omega, k) = \sqrt{2\pi} [\delta(k + \omega)\overline{g}_+(\omega) + \delta(k - \omega)\overline{g}_-(\omega)], \quad (\text{D9})$$

where

$$\overline{g}_\pm(\omega) \stackrel{\text{def}}{=} \frac{1}{\sqrt{2\pi}} \int_{-\infty}^{\infty} du e^{i\omega u} g_\pm(u). \quad (\text{D10})$$

Taking the inverse transform of Eq. (D9), one obtains for the general solution to Eq. (D7)

$$g(x, t) = \frac{1}{\sqrt{2\pi}} \int_{-\infty}^{\infty} d\omega [\overline{g}_+(\omega)e^{-i\omega(t-x)} + \overline{g}_-(\omega)e^{-i\omega(t+x)}]. \quad (\text{D11})$$

APPENDIX E: EXPANSION OF LIGHT STATES IN TENSOR PRODUCTS OF BROAD-BAND COHERENT STATES

Consider the subspace of broad-band coherent states spanned by $a_f^{\dagger n}|0\rangle$, $n = 0, 1, 2, \dots$. It follows from Louisell [7, p. 106] that the unit operator on this subspace is

$$\int |\alpha, a_f\rangle \langle \alpha, a_f| \frac{d^2\alpha}{\pi}. \quad (\text{E1})$$

Next, let F be any set of orthonormal functions $f_j(\omega)$, $j = 1, 2, \dots$. This implies that the set of operators $|\alpha_j, a_{f_j}\rangle \langle \alpha_j, a_{f_j}|$, $j = 1, 2, \dots$, are mutually orthogonal projections. We say a set

of light states is ‘coherently expressible with respect to F ’ if for some set F of orthonormal functions $f_j(\omega)$, $j = 1, 2, \dots$, every state of the set is some weighted sum (or integral) over j and α_j of states of the form

$$\prod_j |\alpha_j, a_{f_j}^\dagger\rangle, \quad (\text{E2})$$

where the product is a tensor product. The unit operator for the vector space of such states coherently expressible with respect to F is then

$$\sum_j \int |\alpha_j, a_{f_j}\rangle \langle \alpha, a_{f_j}| \frac{d^2 \alpha_j}{\pi}. \quad (\text{E3})$$

Subtleties of coherent states in infinite dimensional vector spaces are touched on in [18, pp. 503–512].

APPENDIX F: MATLAB PROGRAMS FOR SECTION 10

Here we record the MATLAB scripts and functions used to generate Fig. 7.

(1) `Partfn.m` starts the calculation by preparing a list `yList` of the partitions of integers needed for Eq. (C42). It stores `yList` in a file `Part.mat`. It needs to be run only once, with a value of `nmax = floor(3 * mu_max + 16)`, where `mu_max` is the highest value of μ covered. (For `nmax = 32`, `Partfn.m` takes 20 minutes on a Pentium-4 desktop computer.)

(2) `muRun.m` generates data in the cell variable `muResult` for later plotting. It has a section that is easily modified in order to zoom in on one or another parameter region. This part takes values for p_{dark} , η_{det} and η_{trans} for each detector. It takes the parameter `vsq` = $|v|^2$ that is the fraction of energy tapped by the eavesdropper. Finally it takes a parameter for the order of Rényi entropy considered in calculating the eavesdropper’s entropy. (Caution: stronger eavesdropping attacks are expected to be implemented in the future.) In order to speed calculations, it calls `Xifn.m` to pre-compute values of $\Xi(\zeta, n)$, and it also computes a list of all $n!$ for $n = 0, \dots, \text{nmax}$.

(3) `EntPlts.m` plots families of curves, such as that shown in Fig. 7, working from

`muResult`, obtained either from immediately prior running of `muRun.m` or from loading a previously saved `muResult`.

The rest of the scripts and functions are called directly or indirectly by `muRun.m`:

- (4) `muScript.m` is a macro called three times by `muRun.m`.
- (5) `Xifn.m` pre-computes a list of values of $\Xi(\zeta, n)$ and stores them in `XiAr`, in order to speed the computation of probabilities.
- (6) `AvEntfn.m` computes Eq. (10.10).
- (7) `Tfn.m` supports either (10.59) or (10.60) by computing (10.39) or (10.55), respectively, as specified by `CaseCode`, using `Ffn.m`. (So far, the only energy distribution implemented is the Poisson energy distribution, for which $C_n = e^{-\mu} \mu^n / n!$.)
- (8) `Ffn.m` computes either (10.49) or (10.55), as specified by `CaseCode`.
- (9) `Gkmfn.m` is called by `Ffn.m` to compute Eq. (10.49); it uses (global) `XiAr`, `CaseSetUp`, and `gamTab` set up by `muRun.m`. It calls `sumfn.m`.
- (10) `sumfn.m` is a summing routine for efficient calculation of sums in which the ratio of successive terms is pre-computed.
- (11) `Gnfn.m` is called by `Ffn.m` to compute Eq. (10.58).
- (12) `Gmu_kmfn.m` computes Eq. (10.61) for the special case of $C_n = e^{-\mu} \mu^n / n!$.
- (13) `Gmufn.m` computes Eq. (10.63) for the special case of $C_n = e^{-\mu} \mu^n / n!$.
- (14) `GCfn.m`. Not yet implemented.

Here is the code for all these except `GCfn.m`, not yet implemented.

MATLAB PROGRAMS

(1) Partfn.m

```
function[] = Partfn(nmax)
% 26 OCT 04
% sets up cell for partitions from  $n = 1$  to  $n = nmax$ 
% assumes  $nmax > 2$ 
% test and run for  $nmax = 32$  on 26 Oct 04 (took 20 minutes)
yList = cell(1,nmax);
yList{1} = [1];
yList{2} = [0 1;2 0];
for jcell = 3:nmax
yList{jcell} = Upfn(yList{jcell-1});
end
save Part.mat yList % ESSENTIAL RESOURCE!

function[y] = Upfn(Ar)
% Used in generating partitions of  $n + 1$  from partitions of  $n$ ;
% Ar has a row for each  $\nu$  vector of partitions of  $n$ .
temp = size(Ar);
oneCol = ones(temp(1),1);
zeroPad = zeros(size(Ar));
oneColPadded = [oneCol zeroPad]; % row width is  $n + 1$ 
zeroCol = zeros(temp(1),1);
ArPadded = [Ar zeroCol]; % add a column to get  $n + 1$  columns
ArP1 = ArPadded + oneColPadded;
% Up proper
for jRow = 1:temp(1)
    for j = 1:temp(2)
        if Ar(jRow,j) > 0
            Vec = ArPadded(jRow,:);
            Vec(j) = Vec(j)-1;
            Vec(j+1) = Vec(j+1)+1;
            ArP1 = [Vec;ArP1];
        end % of If
    end % of For j
end % of For jRow
ArP1 = sortrows(ArP1);
tempz = size(ArP1);
y = ArP1(1,:);
for jRow = 2:tempz(1)
    if ArP1(jRow-1,:) == ArP1(jRow,:)
    else
        y = [y;ArP1(jRow,:)];
    end % of If
end % of For jRow
```

(2) muRun.m

```
% Compute and store and plot  $\mu$ -dependence of figure of merit
% and pGood, pSiftErr, and AvEnt
% Define figure of merit = pGood .* AvEnt
% 1 NOV 04
global alpha0 dark vsq CaseSetUp zetaVec XiAr NsqFac yList

% ***** VARY TO DEFINE CASE *****

etaDet = [0.1 0.1 0.1 0.1] ;
%etaDet = [1 1 1 1] ;
etaTrans = [1 1 0.1 0.1];
%etaTrans = [1 1 1 1];
dark = 5.*10^(-5) .* [1 1 1 1];
%dark = [0 0 0 0];
alpha0 = 1-etaDet .* etaTrans;
vsq = .25; % vsq is fraction of Bob's energy tapped by Evang.
%vsq = 0;
zetaVec = [1 10 100 1000]; % Row vector (1, length(zetaVec)) For Case
Ry = 1.1; % Order of Renyi entropy
% can put in knob variables later
% need to make global array of  $|C_n|^2$  if cases 5, 6 used.
% parameters for range and fineness of  $\mu$ 
fine_incr = .0001;
mu_begin = 0; % may add a little to avoid problem when  $p_{\text{dark}} = 0$ ;
mu_fine_max = .007;
n_fine_max = floor((mu_fine_max - mu_begin)/fine_incr);
mu_max = 0.04;
incr = .002; % increment  $\mu$  after first steps of incr/n_fine_max
n_incr_max = 1 + floor((mu_max - mu_begin -
n_fine_max*fine_incr)/incr);
%mu_max = (n_incr_max+1)*incr
muVec = zeros(1,n_incr_max+n_fine_max+1); % will be loaded with  $\mu$  values

% ***** END OF CASE DEF *****

CaseSetUp = cell(1,6);
CaseSetUp{1} = etaDet;
CaseSetUp{2} = etaTrans;
CaseSetUp{3} = dark;
CaseSetUp{4} = vsq;
CaseSetUp{5} = zetaVec; % row vector
CaseSetUp{6} = Ry; % Renyi entropy of order Ry. load Part.mat

nmax = 32;
if ((zetaVec == zetaVecOld) & (nmax == nmaxOld))
else
XiAr = Xifn(zetaVec,nmax,yList); % assumes yList on hand
```

```

%XiAr = cell(1,nmax+1);
% cell{n+1} is Xi(zeta,n), a column vector (1,length(zetaVec))
zetaVecOld = zetaVec;
nmaxOld = nmax;
end
% set up table of factorials to speed calculation
global gamTab
gamTab = cell(1,nmax+1);
for kk = 1:33
gamTab{kk} = factorial(kk-1);
end
% END of setUp.m

% GET LIMITS for muMeritLims
CaseRestore = CaseSetUp{5};
CaseSetUp{5} = 0;
muScript
    pGoodZ0 = pGood;
AvEntZ0 = AvEnt;
FigMerZ0 = FigMer;
pSiftErrZ0 = pSiftErr;
CaseSetUp{5} = 10^50;
muScript
    pGoodZInf = pGood;
AvEntZInf = AvEnt;
FigMerZInf = FigMer;
pSiftErrZInf = pSiftErr;

% Get in-between values of zeta
CaseSetUp{5} = CaseRestore;
muScript

muResult = cell(1,5);
muResult{1} = CaseSetUp;
muResult{2} = [pGoodZ0;pGood;pGoodZInf;muVec];
muResult{3} = [AvEntZ0;AvEnt;AvEntZInf;muVec];
muResult{4} = [FigMerZ0;FigMer;FigMerZInf;muVec];
muResult{5} = [pSiftErrZ0;pSiftErr;pSiftErrZInf;muVec];

% next can be run separately as EntPlts
    FigMerPlt = muResult{4};
plot(muVec, FigMerPlt(2,:))
    xlabel('mu')
    ylabel('FigMerit')
    title('FigMerit vs. mu; zeta = 0; zeta = inf --')
    text(.5,.05, '\itp_{\rm dark} = 0, \eta_{\rm
det} = 0.1, \eta_{\rm Trans} = 1.')

```

(3) EntPlts.m

```
% Program For plotting data In muResult gotten from running muRun or
% loading muResult
% Plots choice of "kind".
% 6 NOVEMBER 2004
kind = input('1 for pGood, 2 for AvEnt, 3 for FigMer, 4 for
pSiftErr')
% takes  $\mu$  values as vector muX, an edited muVec taken from edited muResult
pltVec = muResult{kind+1};

% ***** VARY UNTIL next asterisks TO EDIT

startDim = size(pltVec);

% pltVec(:,40:startDim(2)) = []; %** TEMPORARY; comment OUT
pltVec(:,1:20)=[ ];
% *****
tempDim = size(pltVec);
muX = pltVec(tempDim(1),:); % retrieves (edited) muVec
% kind = 1 gets pltVec = pGood
% kind = 2 gets pltVec = AvEnt
% kind = 3 gets pltVec = FigMer
% kind = 4 gets pltVec = pSiftErr
CasePlt = muResult{1}; % CaseSetUp For data In muResult
etaDetPlt = CasePlt{1};
etaTransPlt = CasePlt{2};
darkPlt = CasePlt{3};
vsqPlt = CasePlt{4};
RyPlt = CasePlt{6};

pdarkStr =
['[',num2str(darkPlt(1))',' ',num2str(darkPlt(2))',' ',...
num2str(darkPlt(3))',' ',num2str(darkPlt(4))',' '];
etaDetStr =
['[',num2str(etaDetPlt(1))',' ',num2str(etaDetPlt(2))',' ',...
num2str(etaDetPlt(3))',' ',num2str(etaDetPlt(4))',' '];
etaTransStr =
['[',num2str(etaTransPlt(1))',' ',num2str(etaTransPlt(2))',' ',...
',',num2str(etaTransPlt(3))',' ',num2str(etaTransPlt(4))',' '];

Titles = cell(1,4);
Titles{1} = 'Prob. of correct, sifted bit vs. mu';
% factor of 1/2 For prob of correct basis
Titles{2} = ...
['Evangeline's AvEnt for correct, sifted bits vs. mu; R =
',... num2str(RyPlt)];
Titles{3} = 'FigMerit vs. mu';
Titles{4} = 'prob. of error in sifted bits vs. mu';
```

```

Ylab = cell(1,4);
Ylab{1} = 'pGood';
Ylab{2} = 'Evangeline AvEnt';
Ylab{3} = 'FigMerit';
Ylab{4} = 'pSiftErr';
%plot(muX,pltVec)
plot(muX,pltVec(1,:),muX,pltVec(2,:), '--',muX,pltVec(3,:), '-
.',...
muX,pltVec(4,:), '- ',muX,pltVec(5,:), '- ',muX,pltVec(6,:), '- ')
    xlabel('mu')
    ylabel(Ylab{kind})
    title(Titles{kind})
    axis([0 max(muX) -inf inf])
gtext(['\itp_{\rm dark} = ',pdarkStr,...
'\it, \eta_{\rm det} = ',etaDetStr, '\it, \eta_{\rm trans} =
'...,etaTransStr,', vsq = ',num2str(vsqPlt)])

%muResult = cell(1,5);
%muResult{1} = CaseSetUp;
%CaseSetUp = cell(1,6);
%CaseSetUp{1} = etaDet;
%CaseSetUp{2} = etaTrans;
%CaseSetUp{3} = darkPlt;
%CaseSetUp{4} = vsq;
%CaseSetUp{5} = zetaVec; % row vector
%CaseSetUp{6} = Ry; % Renyi entropy of order Ry

%muResult{2} = [pGoodZ0;pGood;pGoodZInf];
%muResult{3} = [AvEntZ0;AvEnt;AvEntZInf];
%muResult{4} = [FigMerZ0;FigMer;FigMerZInf];
%muResult{5} = [pSiftErrZ0;pSiftErr;pSiftErrZInf];

```

(4) muScript.m

```
% 2 Nov 04 for use by muRun.m
    zVecLen = length(CaseSetUp{5});
pGood = zeros(zVecLen,n_incr_max+1+n_fine_max);
% +1 so ForLoop starts at 1 with  $\mu \approx 0$ 

AvEnt = pGood; % same format
pSiftErr = pGood; % again same format
% Ry order of Renyi entropy from muRun
% Do fine steps at beginning
% mu = .00001; % sloppy fix of problem with  $\mu = 0$  when  $p_{\text{dark}} = 0$ 
mu = 0;
    for kt = 1:n_fine_max
        t0110 = Tfn([2 mu],[0 1 1 0]);
        t1001 = Tfn([2 mu],[1 0 0 1]);
        t1010 = Tfn([2 mu],[1 0 1 0]);
        t0101 = Tfn([2 mu],[0 1 0 1]);
        pGood(:,kt) = t0110 + t1001;
        AvEnt(:,kt) = AvEntfn([2 mu],Ry);
        pSiftErr(:,kt) = (t1010 + t0101)./(t0101+t0110+t1001+t1010);
        FigMer = pGood .* AvEnt;
        muVec(kt) = mu;
        mu = mu+incr/n_fine_max;
    end

mu = mu-.00001; % don't need fix  $\mu > 0$ 
    for kt = n_fine_max+1:n_incr_max+1+n_fine_max
        t0110 = Tfn([2 mu],[0 1 1 0]);
        t1001 = Tfn([2 mu],[1 0 0 1]);
        t1010 = Tfn([2 mu],[1 0 1 0]);
        t0101 = Tfn([2 mu],[0 1 0 1]);
        pGood(:,kt) = t0110 + t1001;
        AvEnt(:,kt) = AvEntfn([2 mu],Ry);
        pSiftErr(:,kt) = (t1010 + t0101)./(t0101+t0110+t1001+t1010);
        FigMer = pGood .* AvEnt;
        muVec(kt) = mu;
        mu = mu+incr;
    end
end
```

(5) Xifn.m

```
function[XiAr] = Xifn(zeta,nmax,yList)
%XiAr(m,n+1) = Xi(zeta(m),n)
% yList in ~/matlab/qed/Part.mat
%(Before running Xifn. load Part.mat)
% 1 NOV 04
% 26 October 04 Preliminary test gets OK limits
% 30 OCT Made XiAr into cell(1,nmax+1) to get enough dynamic range
% kappaAr(m,n) = kappa(zeta(m),n)
% Accepts a vector of values of zeta
% Fails if nmax > nmax used in running partfn.m
% use in loop for Xi(zeta(m),0) ... Xi(zeta(m),nmax) by
% XiAr(m,1) ... XiAr(m,nmax+1)
zlen = length(zeta);
% *XiAr = zeros(zlen,nmax+1);
XiAr = cell(nmax+1); % allows much bigger range of values than array does
XiAr{1} = ones(zlen,1);
XiAr{2} = ones(zlen,1);
kappaAr = kappafn(zeta,nmax);
if nmax < 3
return
else
for ncc = 3:nmax+1
XiAr{ncc} = zeros(zlen,1);
Lst = yList{ncc-1};
dims = size(Lst);
jmax = dims(1);
for j = 1:jmax
XiAr{ncc} = XiAr{ncc}+termfn(Lst(j,:),kappaAr);
end% For j
end% For ncc
end% If nmax

function[kappaAr] = kappafn(zeta,nmax)
% kappa(zeta(m),n)
% 1 NOV 04
% Accepts a vector of values of zeta
% kappaAr(m,n) = kappa(zeta(m),n)
% kappa(zeta,n) = R(zeta,n)./sqrt(zeta^2+1)
x = zeta.^2;
R = zeros(nmax,length(zeta)); % will be transposed later
R(2,:) = ones(1,length(zeta));
pvec = x./(4.*(x+1));
for nct = 3:nmax
R(nct,:) = 1./(1-pvec.*R(nct-1,:));
end
```

```

kappaAr = R * diag(1./sqrt(x+1));
kappaAr(1,:) = ones(1,length(zeta));
kappaAr = kappaAr'; %'
% checked asymptotic --> 2/(sqrt(x + 1) + 1) as  $n$  gets big

function[yCol] = termfn(vec,kappaAr)
% does Column over zeta(m) For one term where vec is a partition of  $n$ 
% For  $n \leq 32$ 
% using kappaAr(m,n) = kappa(zeta(m),n)
n1 = length(vec);
dims = size(kappaAr);
zlen = dims(1);
yCol = ones(zlen,1);
for j = 1:n1
yCol = (kappaAr(:,j)./j).^vec(j)/factorial(vec(j)).*yCol;
end
yCol = yCol.*factorial(n1);

```


(6) AvEntfn.m

```
function[z_out] = AvEntfn(CaseCode,R)
% Assumes CaseCode is [2 mu] or [3 n]
% 29 October put in "if t1001 + t0110 > 0" to get rid of 0/0; untested
% 30 OCT 2004 get zeta from setUp
global CaseSetUp
if CaseCode(1)==2 % BIG BLOCK
    mu = CaseCode(2);
    kmax = 16+3.*mu; % from study with poisfn.m
    % numerator = 0;
    zVecLen = length(CaseSetUp{5});
    numerator = zeros(zVecLen,1);
    for k = 0:kmax
        mmax = kmax - k;
        for m = 0:mmax
            t1001 = Tfn([5 mu k m],[1 0 0 1]);
            t0110 = Tfn([5 mu k m],[0 1 1 0]);
            if t1001+t0110 > 0
                pEv = t1001/(t1001+t0110);
                y = log(pEv.^R + (1-pEv).^R)/((1-R)*log(2));
                numerator = numerator + (t1001+t0110).*y;
            end% if t1001+t0110...
        end% for m
    end% for k
    denom = Tfn([2 mu],[1 0 0 1]) + Tfn([2 mu],[0 1 1 0]);
    z_out = numerator./denom;
else % BIG BLOCK
    % assume [3 n]
    n = CaseCode(2);
    numerator = 0;
    for k = 0:n
        for m = 0:n-k
            t1001 = Tfn([6 n k m],[1 0 0 1])
            t0110 = Tfn([6 n k m],[0 1 1 0])
            if t1001 + t0110 > 0
                pEv = t1001/(t1001+t0110);
                y = log(pEv.^R + (1-pEv).^R)/((1-R)*log(2));
                numerator = numerator + (t1001+t0110).*y;
            end% if t1001 + t0110...
        end% for m
    end% for k
    denom = Tfn([3 n],[1 0 0 1]) + Tfn([3 n],[0 1 1 0]);
    z_out = numerator./denom;
end % BIG BLOCK
```

```

%function[y_out] = Tfn(CaseCode,nVec)
% \mathcal{T} for various cases
%% nVec is negatively coded bit vector; this restricted implementation fails if nVec has
%% more than 4 zeros.

% Casecode can be [1 Cpt] [2 mu] [3 n] [4 Cpt k m] [5 mu k m]
% [6 n k m]
% Cpt is a real number or integer that points to an array Cvec of coefficients.

```

(7) Tfn.m

```
function[y_out] = Tfn(CaseCode,nVec)
% \mathcal{T} for various cases
% 19 OCT 04
% Casocode can be [1 Cpt] [2 mu] [3 n] [4 Cpt k m] [5 mu k m]
% [6 n k m]
% Cpt is a real number or integer that points to an array CVec of coefficients.

% nVec is negatively coded bit vector; this restricted implementation fails if nVec has more
% than 4 zeros.

ctab = [0 0 0 0; 1 0 0 0; 0 1 0 0; 1 1 0 0;...
        0 0 1 0; 1 0 1 0; 0 1 1 0; 1 1 1 0;...
        0 0 0 1; 1 0 0 1; 0 1 0 1; 1 1 0 1;...
        0 0 1 1; 1 0 1 1; 0 1 1 1; 1 1 1 1];

% set up Index as vector that shows where the zeros in nVec are located
% Ctr gets incremented to the number of zeros in nVec.
temp = size(nVec);
dim_nVec = temp(2);
dim_Ctr = dim_nVec - sum(nVec);
jIndex = 0;
if dim_Ctr == 0 % starts big block
    y_out = (-1)^sum(nVec).* Ffn(CaseCode,nVec);
else
    y_out = 0;
    Index = zeros(1,dim_Ctr);
    nxtVec = nVec;
    for jt = 1:dim_nVec
        if nVec(jt)==0
            jIndex = jIndex+1;
            Index(jIndex) = jt;
        end % If nVec
    end % For jt
    % Index [checked and works]
    for jt = 1:2^dim_Ctr
        for jtt = 1:dim_Ctr
            nxtVec(Index(jtt)) = ctab(jt,jtt);
        end % For jtt
        % nxtVec [checked and works]
        y_out = y_out + Ffn(CaseCode,nxtVec);
    % jt_report = jt % * drop in production
    end % For jt
end % of big block
y_out = (-1)^sum(nVec).* y_out;
```

(8) Ffn.m

```
function[z_out]= Ffn(CaseX,nVecX)
% \mathcal{F} – function for various cases. Casecodes [1 Cpt] [2 mu] [3 n]
% [4 Cpt k m] [5 mu k m] [6 n k m]
% Cpt is a real number or integer that points to an array Cvec of coefficients.
% called by Tfn.m which supplies CaseX and nVecX.
global alpha0 dark vsq % supplied by muRun or by setUp.m
alpha = ones(1,4);
darkfac = 1;
usq = 1-vsq;
for kt = 1:4
    if nVecX(kt)==1
        alpha(kt) = alpha0(kt);
        darkfac = - darkfac .*(1-dark(kt)); % might vectorize later
    end % If nVecX
end % For kt
w = alpha(1).*alpha(4).*usq;
x = alpha(1).*vsq;
y = alpha(2).*alpha(3).*usq;
z = alpha(2).*vsq;
switch CaseX(1)
case 1
z_out = GCfn(w,x,y,z); % NOT YET IMPLEMENTED
case 2
    mu_arg = CaseX(2);
z_out = Gmufn(mu_arg,w,x,y,z);
case 3
    n_arg = CaseX(2);
z_out = Gnfn(n_arg,w,x,y,z);
case 4
    k_arg = CaseX(2);
    m_arg = CaseX(3);
z_out = GCKmfn(k_arg,m_arg,w,x,y,z); % assumes global \mathbf{C}
case 5
    mu_arg = CaseX(2);
    k_arg = CaseX(3);
    m_arg = CaseX(4);
z_out = Gmu_kmfn(mu_arg,k_arg,m_arg,w,x,y,z);
case 6
    n_arg = CaseX(2);
    k_arg = CaseX(3);
    m_arg = CaseX(4);
z_out = Gnkmfn(n_arg,k_arg,m_arg,w,x,y,z);
otherwise
end
z_out = z_out .* darkfac;
```

(9) Gkmfn.m

```

function[y_out] = Gnmfn(n,k,m,w,x,y,z)
% 4 NOV 04
% "vectorize" over w, x, y, z as well as over zetaX
% works only if 32 \ge n \ge k + m
% implemented to assume zeta = \infty if zeta \ge 10^40
% gamTab{n+1} = factorial(n) For 0 \le n \le 32 (think gamma function).

global XiAr CaseSetUp gamTab
zetaX = CaseSetUp{5};
if zetaX==0% BIG BLOCK
    a0 = (gamTab{n-k+1}/(gamTab{n-k-m+1}*gamTab{m+1}*(n+1)))...
    .*x.^k.*z.^m.*y.^(n-k-m);
    if n-k-m==0
        y_out = a0;
    else
        avec = ones(1,n-k-m+1);
        avec(1) = a0;
        for jt =1:n-k-m
            avec(jt+1) = (jt+k)*(n-k-m+1-jt)/((n-k+1-jt)*jt);
        end% For jt
        xt = w./y;
        y_out = sumfn(avec,xt);
    end% If n-k-m==0
else if zetaX < 10^40 % General Case
    zlen = length(zetaX);
    NsqFac = zeros(zlen,1);
    for jt = 0:n
        NsqFac = NsqFac + XiAr{jt+1}.*XiAr{n-
jt+1}./(gamTab{jt+1}*gamTab{n-jt+1});
    end% For jt
    NsqFac = (gamTab{n+1})*NsqFac;
    NsqFac = 1./NsqFac;
    Const = NsqFac.*(gamTab{n+1}/(gamTab{m+1}*gamTab{k+1}))*...
    (x.^k.*z.^m.*y.^(n-k-m));
    Tot = zeros(zlen,length(w));
    for j = 0:n-k-m
        Tot = Tot + XiAr{j+k+1}.*XiAr{n-k-j+1}*(w./y).^j./...
        (gamTab{j+1}*gamTab{n-k-m-j+1});
    end% For j
    y_out = Tot.*Const;
else % limit as zeta --> \infty
    y_out = 2^(-n)*gamTab{n+1}.*x.^k.*z.^m.*(w+y).^(n-k-
m)./...
    (gamTab{k+1}*gamTab{m+1}*gamTab{n-k-m+1});
end
end % BIG BLOCK

```

(10) sumfn.m

```
function[y] = sumfn(ar,x)
    % ar is a vector of the form [a_0,a_1/a_0,a_2/a_1,...,a_n/a_{n-1}]
    % x is a variable value or a vector of variable values
    % y = sum_{j=0}^n a_j.*x.^j.
    dimar = size(ar);

    ntemp = dimar(2); % biggest n is ntemp - 1;
    % set up ztemp
    dimx = size(x);
    nxtemp = dimx(2);
    ztemp = ones(1,nxtemp);
    for ct = ntemp:-1:2 % trouble if ntemp < 2.
        y = x.*ar(ct).*ztemp;
        ztemp = 1+y;
    end
    y = ar(1).*ztemp;
    % test by ar = [2 1.2 1.2 1.2 1.2], x = [2 3 4]
    % sumfn([2 1.2 1.2 1.2 1.2],[2 3 4]) Checks.
```

(11) Gnfn.m

```
function[y_Gn] = Gnfn(n_arg,w,x,y,z)
% 26 OCT 04 % does limit of zeta --> \infty if zetaX > 10^40
% 29 OCT tested general zetaX against limits OK.
% Old Gnfn(zetaX,n_arg,w,x,y,z)
global XiAr CaseSetUp gamTab
x1 = (y+z);
x2 = (w+x);
zetaX = CaseSetUp{5};
if zetaX == 0
    if x1 == x2
        y_Gn = x1.^n_arg;
    else
        y_Gn = (x1.^(n_arg+1)-x2.^(n_arg+1))./((n_arg+1).*(x1-x2));
    end% If x1
else
    if zetaX < 10^40
        zlen = length(zetaX);
        NsqFac = zeros(zlen,1);
        for j_t = 0:n_arg
            NsqFac = NsqFac + XiAr{j_t+1}.*XiAr{n_arg-j_t+1}./...
                (gamTab{j_t+1}*gamTab{n_arg-j_t+1});
        end% For j_t
        NsqFac = (gamTab{n_arg+1}).*NsqFac;
        NsqFac = 1./NsqFac;
        Const = NsqFac*(y+z).^n_arg;

% Modified from Gnkmfn
        Tot = zeros(zlen,length(w));
        for j = 0:n_arg
            Tot = Tot + XiAr{j+1}.*XiAr{n_arg-j+1}*...
                ((w+x)./(y+z)).^j./(gamTab{j+1}*gamTab{n_arg-j+1});
        end% For j
        Tot = gamTab{n_arg+1}.*Tot;
        y_Gn = Tot.*Const;
    else % limit as zeta --> \infty
        y_Gn = ((x1+x2)./2).^n_arg;
    end% If zetaX < 10^40
end
```

(12) Gmu_kmfn.m

```
function[y_ans] = Gmu_kmfn(mu_arg,k_arg,m_arg,w,x,y,z)
% 30 OCT 04
global CaseSetUp gamTab
zetaX = CaseSetUp{5};
% checked sum against Gmufn, OK.
if zetaX < 10^40 % zeta \ge 10^40 treated as infinite
    nmax = floor(3*mu_arg+16);
    y_ans = 0;
    for nt = k_arg + m_arg:nmax
        incr = Gnkmfn(nt,k_arg,m_arg,w,x,y,z);
        y_ans = y_ans + mu_arg^nt.*incr./gamTab{nt+1};
    end % For nt
    y_ans = exp(-mu_arg).*y_ans;
else % limit as zeta --> \infty
    mu2 = mu_arg/2;
    y_ans = exp(-mu2.*(2-w-y)).*(mu2.*x).^k_arg.*(mu2.*z).^m_arg./...
        (gamTab{k_arg+1}*gamTab{m_arg+1});
end
```


(13) Gmufn.m

```
function[y_out] = Gmufn(mu_arg,w,x,y,z);
global CaseSetUp gamTab
%gamTab{n+1} = factorial{n} For n = 0, ..., nmax
zetaX = CaseSetUp{5};
if zetaX == 0
    x1 = (y+z);
    x2 = (w+x);
    if mu_arg == 0
        y_out = 1;
    else
        if x1 == x2
            y_out = exp(-mu_arg.*(1-x1));
        else
            y_out = exp(-mu_arg).*(exp(mu_arg.*x1)
                -exp(mu_arg.*x2))./...(mu_arg.*(x1-x2));
        end% If x1 == x2
    end% If mu_arg == 0
else if zetaX > 10^40
    y_out = exp(-mu_arg.*(2-w-x-y-z)./2);
else % General Case 0 < zetaX \le 10^40
    y_out = zeros(length(zetaX),length(w));
    % column vector of same length as zetaX
    nmax = floor(3*mu_arg+16);
    for nt = 0:nmax
        incr = Gnfn(nt,w,x,y,z);
        y_out = y_out + mu_arg^nt.*incr./gamTab{nt+1};
    % gamTab{nt+1} = factorial(nt)
    end% For nt
    y_out = exp(-mu_arg).*y_out;
end % General Case
end
```

-
- [1] J. M. Myers, “Polarization-entangled light for quantum key distribution: how frequency spectrum and energy affect detection statistics,” to appear in *Proceedings of SPIE*, Vol. 5815, Quantum Information and Computation III, E. Donkor, A. R. Pirich, H. E. Brandt, Eds. (SPIE, Bellingham, WA, 2005).
- [2] F. H. Madjid and J. M. Myers, “Matched detectors as definers of force,” arXiv:quant-ph/0404113 v2, 2004; accepted for publication in *Annals of Physics*.
- [3] J. von Neumann, *Mathematical Foundations of Quantum Mechanics* (Princeton University Press, Princeton, 1955).
- [4] J. M. Myers and F. H. Madjid, “A proof that measured data and equations of quantum mechanics can be linked only by guesswork,” pp. 221–244 in *Quantum Computation and Information*, edited by S. J. Lomonaco, Jr. and H. E. Brandt, Contemporary Mathematics Series, Vol. 305 (American Mathematical Society, Providence, RI, 2002).
- [5] J. M. Myers and F. H. Madjid, “Gaps between equations and experiments in quantum cryptography,” *J. Opt. B: Quantum Semiclass. Opt.* **4**, S109–S116 (2002).
- [6] H. P. Yuen and J. H. Shapiro, “Optical communication with two-photon coherent states—Part I: quantum-state propagation and quantum-noise reduction,” *IEEE Trans. Info. Theory* **IT-24**, 657–668 (1978).
- [7] W. H. Louisell, *Quantum Statistical Properties of Radiation* (Wiley, New York, 1973).
- [8] G. Sewell, *Quantum Mechanics and Its Emergent Macrophysics* (Princeton University Press, Princeton, NJ, 2002).
- [9] N. I. Akhiezer and I. M. Glazman, *Theory of Linear Operators in Hilbert Space* (Ungar, New York, Vol. I, 1961; Vol. II, 1963).
- [10] L. Mandel and E. Wolf, *Optical Coherence and Quantum Optics* (Cambridge University Press, New York, 1995).
- [11] J. D. Jackson, *Classical Electrodynamics*, 2nd ed., chap. 7 (Wiley, New York, 1975).
- [12] L. Brillouin, *Wave Propagation and Group Velocity* (Academic Press, New York, 1960).

- [13] J. Peřina, Jr., O. Haderka, and J. Soubusta, “Quantum cryptography using photon source based on postselection from entangled two-photon states,” *Phys. Rev. A* **64**, 052305 (2001); also in arXiv:quant-ph/0107086 (2001).
- [14] A. K. Ekert, “Quantum cryptography based on Bell’s theorem,” *Phys. Rev. Lett.* **67**, 661–663 (1991).
- [15] F. A. Bovino, P. Varisco, A. Martinoli, P. De Nicolo, S. Bruzzo, A. M. Colla, G. Castagnoli, G. di Giuseppe, and A. V. Sergienko, “Demonstration of secure quantum key distribution,” pp. 1–10 in *Proceedings of SPIE*, Vol. 5105, Quantum Information and Computation, E. Donkor, A. R. Pirich, H. E. Brandt, Eds. (SPIE, Bellingham, WA, 2003).
- [16] Bateman Manuscript Project, *Higher Transcendental Functions* (McGraw-Hill, New York, 1953), Vol. I, pp. 56–57.
- [17] S. Sternberg, *Group Theory and Physics* (Cambridge University Press, New York, 1994), pp. 76–78.
- [18] J. M. Jauch and F. Rohrlich, *The Theory of Photons and Electrons*, 2nd ed. (Springer-Verlag, New York, 1974).